# An Investigation of Counterrotating Tip Vortex Interaction

R.K. Majjigi, K. Uenishi, and P.R. Gliebe

GE Aircraft Engines Advanced Engineering Technologies Department Cincinnati, Ohio 45215

October 1989

Prepared for

Lewis Research Center Under Contract NAS3-24080



(NASA-CR-185135) AN INVESTIGATION OF COUNTERROTATING TIP VORTEX INTERACTION (GE) CSCL 20A N90-11549

Unclas 63/71 0234874

<del>-</del>	· · · · · · · · · · · · · · · · · · ·		 	
		• • • -		
				-
				-
				***
				₹.

#### **Summary**

A tip vortex interaction model that was originally developed for compressors has been extended and adapted for use with counterrotating open rotors. This report documents the analytical modeling, model evaluation with limited experimental data, and certain key parametric studies pertaining to the tip vortex as a noise-source mechanism for the unsteady loading noise of counterrotating propfan propulsors. The existing, simple, basic model can be extended toward establishing a more sophisticated, complete model in the future. Particularly, the empirical constants used in the model can be further modified and improved once detailed tip vortex aerodynamics and acoustic data become available through controlled experimental studies.

,			
			-
			-
		•	
			1
		•	
			-
		· · · · · ·	
		<del>.</del>	
		•	

## **Table of Contents**

Section		Page
1.0	Introduction	1
	1.1 Statement of the Problem and Method of Approach	
	1.2 Literature Survey	2
2.0	Counterrotating Blade Tip Vortex Model	3
	2.1 Mathematical Description	3
	2.2 Empirical Relationships	8
3.0	Model Evaluation	17
	3.1 Parametric Studies	17
	3.1.1 Influence of Tip Vortex Strength and Drag	
	3.1.2 Influence of Tangential Location of Tip Vo	rtex 26
	3.1.3 Influence of Tip Vortex Trajectory	29
	3.1.4 Influence of Decay Rate of Tip Vortex	33
	3.1.5 Influence of Progressive Clipping of Aft Ro	otor 33
	3.2 Data - Predictions Evaluation	38
4.0	Conclusions and Recommendations	52
	4.1 Conclusions	52
	4.2 Recommendations	52
5.0	References	54
6.0	Nomenciature	56
	Appendix A	59

# List of Illustrations

Figure		Page
1.	The Combined Forced (Within the Core) and Free (Outside the Core) Vortex Model for the Tip Vortex.	4
2.	Nature of the Tip Vortex Flow Model for a Ducted Rotor.	5
3.	Comparison of Gust Harmonic Spectra at Three Spanwise Locations for Increasing Values of Tip Clearance and for No Tip Vortex Case.	7
4.	Correlation and Data for the Streamwise Variation of Normalized $(V\theta)_{\text{max}}$ of the Tip Vortex.	10
5.	Correlation and Data for the Streamwise Variation of Normalized Radius of the Tip Vortex Core.	10
6.	Representative Correlation and Data for the Streamwise Variation of Normalized $(V\theta)_{max}$ , Radius, and Circulation of the Tip Vortex.	11
7.	Streamwise Variation of Normalized Circulation of the Tip Vortex for Three Different Power Law Decay Rates.	12
8.	Spanwise Variation of the Local Section Lift Coefficient for Takeoff and Cruise Conditions for F-7 Blades.	14
9.	Spanwise Variation of the Chord for the F-7 Blade Design.	14
10.	Correlation and Data for the Trajectory of the Tip Vortex.	15
11.	Planform of the F-7/A-7 Unducted Fan Blade Design, Showing the Extent of Clipping on the Aft Rotor.	18
12.	Schematic of a Narrowband Acoustic Spectrum of a $9 \times 8$ Blade Number Configuration.	20
13.	Predicted Effect of Tip Vortex Strength on Gust Harmonic Spectra with Three Different C <sub>d</sub> Values at the Streamline of 100% Span from the Hub.	21
14.	Predicted Effect of the Tip Vortex Strength on Gust Harmonic Spectra with Three Different C <sub>d</sub> Values at the Streamline of 70.7% Span from the Hub.	22
15.	Predicted Effect of Tip Vortex Strength on Gust Harmonic Spectra with Three Different Ca Values at the Streamline Location of 45.4% Span from the Hub.	23

# List of Illustrations(Continued)

Figure		Page
16.	The Predicted Effect of the Tip Vortex Strength on Interaction Tone SPL Sum with $C_d = 0.005$ .	24
17.	Predicted Effect of the Drag Coefficients on the Interaction Tone SPL Sum with $C_i = 2.0$ .	24
18.	Predicted Tip Vortex Effect of the Drag Coefficients (0.03, 0.02, and 0.005) on Interaction Tone SPL Sum with $C_i = 2.0$ .	25
19.	Predicted Tangential Distribution of Gust Velocity at Three Radial Locations for Various Tangential Locations of Tip Vortex, and for the Case of No Tip Vortex.	27
20.	Predicted Effect of Tangential Location of Tip Vortex on Gust Harmonic Spectra at Three Radial Locations.	28
21.	A Comparison of the Predicted and Measured Individual Interaction Tones.	29
22.	Sensitivity of the Tone SPL Sum of Interaction Noise to the Tangential Location of Tip Vortex.	30
23.	Predicted Influence of the Tip Vortex Trajectory on Gust Harmonic Spectra at Three Streamlines in the Tip Region.	31
24.	Predicted Influence of Tip Vortex Trajectory on Each Interaction Tone at Observer Angle of 91°.	32
25.	Predicted Influence of Tip Vortex Trajectory on Interaction Noise Tone SPL Sum.	32
26.	Predicted Gust Harmonic Spectra at Two Rotor-to-Rotor Spacings for the Tip Vortex at Different Decaying Rates and for the Case of No Tip Vortex at Two Streamline Locations.	34
27.	Assumed Performance of the Progressively Clipped Aft Rotor.	35
28.	Predicted Effect of Progressive Clipping of the Aft Rotor on the Steady Loading and Thickness Noise.	35
29.	Predicted Effect of Progressive Clipping of the Aft Rotor on the Wake/Tip Vortex Interaction Noise.	36

# List of Illustrations (Concluded)

Figure		Page
30.	The Predicted Effect of Progressive Clipping of the Aft Rotor on the OASPL Directivity.	37
31.	Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Steady Loading and Thickness Noise.	39
32.	Comparison of the Measured and Predicted Steady Loading and Thickness Tones for Standard and Clipped Aft Rotor at 105° Observer Angle.	39
33.	Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Interaction Tone SPL Sum With and Without the Tip Vortex Model ( $C_d = 0.02$ , $C_t = 2$ , $K_{vtx} = 2.0$ , $bt/S = 0.5$ ).	40
34.	Comparison of the Effect (Measured and Predicted) of Clipping of the Aft Rotor on Interaction Tone SPL Sum with and without the Tip Vortex Model ( $C_d = 0.005$ , $C_i = 2$ , $K_{vtx} = 2.0$ , $bt/S = 0.5$ ).	41
35.	A Comparison of the Measured and Predicted Effect of the Clipping of the Aft Rotor on Interaction Tone Sum With and Without the Tip Vortex Model ( $C_d = 0.005$ , $C_i = 1$ , $K_{vtx} = 2.0$ , $bt/S = 0.5$ ).	42
36.	A Measured and Predicted Effect Comparison of Clipping of the Aft Rotor on Interaction Tone Sum, With and Without the Tip Vortex Model ( $C_d = 0.005$ , $C_1 = 3$ , $K_{vtx} = 2.0$ , $bt/S = 0.5$ ).	43
37.	Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Individual Interaction Tones, With and Without the Tip Vortex Model ( $C_d = 0.005$ , $C_i = 3$ , $K_{VIX} = 1.0$ , $bt/S = 0.5$ ).	45
38.	The Predicted Spanwise Variation of Normalized Streamwise Distance, Wake Centerline Defect, and Semiwake Width.	<b>4</b> 7
39.	Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Steady Loading and Thickness Noise for 80% rpm.	49
40.	Measured and Predicted Effect of Clipping of the Aft Rotor on Interaction Tone SPL Sum With and Without the Tip Vortex Model ( $C_d = 0.005$ , $C_i = 3$ , $K_{vtx} = 1.0$ , $bt/S = 0.5$ ).	49
41.	Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Individual Interaction Tones with and without the Tip Vortex Model ( $C_d = 0.005$ , $C_1 = 3$ , $K_{vtx} = 1$ , $bt/S = 0.5$ ).	50

#### 1.0 Introduction

In recent times, the high speed swept-propfan concept has attracted considerable attention from the aircraft industry (Reference 1). This is due to the higher propulsion efficiencies and a correspondingly lower sfc (specific fuel consumption) at high cruise Mach numbers (typically  $M \approx 0.8$ ), compared to the modern high bypass turbofan engines. Application of two counterrotating, swept propellers to extract the swirl energy that would be lost in the case of a single propeller is expected to yield even higher levels of propulsion efficiency. The development of acoustic technology to understand the noise characteristics of this new propulsion concept is an important aspect in the design phase; hence GEAE (GE Aircraft Engines), in cooperation with NASA, has undertaken an extensive scale model program to investigate the influence of various geometric and aerodynamic parameters on the performance and noise characteristics of swept, counterrotating propellers.

## 1.1 Statement of the Problem and Method of Approach

The acoustic signature of a counterrotating propeller is rich in tonal content which can be ascribed to various noise-generating mechanisms at work. The analytical modeling of these mechanisms will enable a better physical understanding which, in turn, will help in evolving a methodology for low noise designs. The principal noise mechanisms associated with the tonal spectrum of a counterrotating propeller are:

- Steady loading and thickness noise of each rotor
- Unsteady loading noise generated by the aft rotor due to an interaction with the wake shed by the forward rotor
- Unsteady loading noise generated by the aft rotor due to an interaction with the tip vortex of the forward rotor
- Unsteady loading noise (generated by either rotor) due to the presence of a rotating potential field of the other rotor.

This report documents work performed on the analytical modeling of the unsteady loading noise due to the tip vortex interaction. The physical process involved in the generation of the tip vortex of these propulsors is similar to that of fixed wings; that is, a static pressure differential between the pressure and suction sides of the airfoil in the tip region of the wing results in a flow from the pressure to the suction side, which ultimately rolls up into a tip vortex. This physical process can be explained using finite wing theory; that is, the effect of a reduction in the wingspan from infinity to a finite length may be viewed as the effect of a removal of tip vortices extending indefinitely in the direction of the span and a replacement of these vortices by trailing vortices connected at the downstream ends by starting vortices (Reference 2).

The analytical modeling of the upwash field (gust) created by the tip vortex of the forward propulsor at the leading edge (or one-fourth chord) of the aft propulsor is based on an approach previously implemented for fan tone noise (References 3 and 4). This approach

consists of modeling the tip vortex as a free vortex (that is,  $\Gamma = \text{constant}$ ,  $V\theta_{\alpha} 1/r$ ) with a forced vortex core (that is, within the core,  $V\theta_{\alpha} r$ ), the strength, size, and streamwise development of which are empirically modeled. The gust field of the tip vortex at the aft rotor determines the unsteady lift response of the aft rotor blade and, hence, the additional unsteady loading noise due to the tip vortex.

#### 1.2 Literature Survey

A survey of existing literature on tip vortices of open-tipped wings (for instance, fixed wings, helicopter rotors) was conducted to aid in understanding the characteristics of such tip vortices (namely, size, strength, trajectory, and decay rate), so that certain empirical relationships could be developed for application to the tip vortex model for an unducted rotor. Unfortunately, very little information could be found in the open literature on tip vortices of highly swept propfans. The literature survey was conducted with the objective of finding experimental information about the following:

- Tip vortex trajectory
- Tip vortex strength such as, circulation or (Vθ )max and size of the core
- Growth/decay of tip vortex with streamwise distance.

Experimental information on the tip vortex trajectory contained in References 5 and 6 relates to helicopter rotors in hover mode. The experimental data was essentially the spanwise coordinate of the tip vortex at different axial stations. The rotors were typical helicopter rotors with large aspect ratio  $(4.5 \le AR \le 18)$  and low hub/tip ratio (HTR = 0.1).

Wind tunnel measurements of a tip vortex shed from a fixed wing at low subsonic speeds (from References 7 and 8) provided the information for developing empirical relationships for the size and strength of the tip vortex. The experimental information on the streamwise development of the tip vortex contained in Reference 8 was used to model the growth/decay of the tip vortex with streamwise distance.

# 2.0 Counterrotating Blade Tip Vortex Model

This section briefly describes the aerodynamic model developed for predicting the gust field at the aft rotor due to the tip vortex of the forward rotor. This data is used to evaluate the fluctuating lift and the associated unsteady loading or interaction noise of the counterrotating propellers. The quasi-3D (quasi-three-dimensional) aerodynamic model of the forward rotor exit flow field employs a streamline-by-streamline approach (References 3 and 4 provide a detailed description). The velocity field induced by the tip vortex of the forward rotor at the aft rotor is computed first for a coordinate system rotating with the forward rotor. A coordinate transformation of this velocity field relative to the aft rotor is performed; this yields the upwash velocity perturbations from the freestream value for the aft rotor. The upwash velocity perturbations exhibit a periodicity coinciding with that of the forward rotor. Fourier analysis of the upwash waveform yields the upwash gust harmonics distribution. The twist of the forward rotor blade from hub to tip causes a time/phase lag between the flow field from the hub and tip regions impinging on the aft rotor blade. This spanwise distortion and clocking of the rotor wake/vortex "sheet" as it convects downstream results in a spanwise phase variation of the wake/vortex field. The analysis for predicting this phase lag due to the twist of the rotor blades was developed under a previous GE IR&D (Independent Research and Development) project and is described in Reference 3. The spanwise distribution of the gust harmonics, along with the above-described aerodynamic phase, gives a complete description of the gust field impinging on the aft rotor.

Computation of the fluctuating lift force on the aft rotor due to the upwash gust is performed next by using the classical (incompressible) unsteady lift response theory of Sears (Reference 9), modified to take compressibility effects into account according to a procedure developed by Amiet (Reference 10). The fluctuating lift force forms the right-hand side of the wave equation, whose formulation and method of solution are beyond the scope of this report. Developed under a GE IR&D project, the acoustic model used in this report is formulated in the frequency domain and computes the tone noise generated by the steady loading and thickness sources of the rotor rows, together with the tone noise resulting from the unsteady loading due to fluctuating lift forces. The fundamental formulation of the model can be found in Reference 11. Subsection 2.1 briefly describes the tip vortex model development, and Subsection 2.2 describes the procedure followed in establishing certain empirical relationships associated with the tip vortex model.

#### 2.1 Mathematical Description

The tip vortex model has evolved from a similar model for computing secondary flow vortices (in and behind a ducted rotor blade passage) which are dominated by the tip clearance leakage flow (References 12 and 13). The tip vortex model assumes the existence of a core that contains all of the shed vorticity, so that the motion outside is irrotational. Figure 1 is a sketch of the radial variation of tangential velocity (V $\theta$ ) induced by the tip vortex and the associated circulation of the vortex. Obviously, even at large distances from the vortex center, sufficiently large swirl velocities exist, in terms of  $V\theta/(V\theta)$ max. It should be noted that the current

tip vortex model does not include an effect of an axial velocity component of the tip vortex; however, this will be included in future work, as detailed data become available.




Figure 1. The Combined Forced (Within the Core) and Free (Outside the Core) Vortex Model for the Tip Vortex.

In the case of the ducted fan rotor, the tip vortex model superimposes a row of combined forced/free vortices and an image row on the opposite side of the annulus wall to enforce the zero normal velocity at the wall. Figure 2 depicts a sketch of unwrapped annulus with both the tip vortices and the image vortices. The vortices are located at a periodic tangential spacing that is equal to the blade spacing. The spanwise and the tangential (+y and +x directions, respectively)velocities outside the tip vortex core were determined by using an extension of Lamb's solution (Reference 14) for the induced flow field about two infinite rows of vortices of finite radius, as modeled (Figure 2). The resulting expressions for the induced velocities outside the domain Rt (tip radius) are written as follows.

For the tangential velocity Wt

$$W_{t} = -\frac{v_{tx}}{2 S} \left[ \frac{\sinh M}{\cosh M - \cos p} - \frac{\sinh N}{\cosh N - \cos p} \right]$$
 (1)

and for the radial velocity Wr

$$W_{r} = -\frac{\Gamma_{vtx}}{2 S} \left[ \frac{\sin p}{\cosh M - \cos p} - \frac{\sin p}{\cosh N - \cos p} \right]$$
 (2)

where

$$M = \frac{2\pi}{S} (y - b_r - \tau) \tag{3}$$

$$N = \frac{2\pi}{S} (y + b_r - \tau) \tag{4}$$

and

$$P = \frac{2\pi}{S} (x - b_t) \tag{5}$$




Figure 2. Nature of the Tip Vortex Flow Model for a Ducted Rotor.

The parameters "x" and "y" are coordinates of the unwrapped annulus (the annulus is unrolled). It can be seen that at y = 0 (that is, at the annulus wall), Equation 1 reduces to:

$$W_{t} \mid y = 0 = \frac{\Gamma_{vtx}}{S} \left[ \frac{\sinh (b_{r} + \tau)}{\cosh (b_{r} + \tau) - \cos p} \right]$$
 (6)

and Equation 2 reduces to:

$$\begin{array}{c|c}
w_r & = 0 \\
y=0
\end{array} \tag{7}$$

For a given value of  $(b_r + \tau)$ , as y increases,  $\sinh M \rightarrow \sinh N$  and  $\cosh M \rightarrow \cosh N$ , and the expressions for tangential and radial velocities created due to the tip vortex approach zero (Equations 1 and 2); thus, implying that as one approaches the hub wall, the tangential and radial velocities created due to the tip vortex vanish, which is physically realistic.

The region within the domain  $R_t$  behaves as a forced vortex (like a solid body of revolution); the domain  $R_t$  is given by:

$$(x - b_{t})^{2} + (y - b_{r} - \tau)^{2} \le a^{2}$$
(8)

where "a" is the radius of the vortex core.

The angular velocity of the tip vortex can be related to the circulation of the tip vortex by:

$$w = \frac{\Gamma_{\text{vtx}}}{2 \pi a^2} \tag{9}$$

For a point P(x,y) within the domain  $R_t$ , the tangential component of the velocity induced by the tip vortex is given by:

$$W_{t} = - \operatorname{wr} \sin \alpha \tag{10}$$

and the radial component by

$$W_r = wr \cos \alpha$$
 (11)

where

$$r = \left\{ (x - b_t)^2 + (y - b_r - t)^2 \right\}^{1/2}$$

and

$$\alpha = \tan^{-1} \left[ \frac{y - b_r - \tau}{x - b_r} \right]$$

Equations 1 through 11 specify the induced velocity field in a radial plane behind the blade trailing edge due to the presence of the tip vortex.

For the unducted fan, the annulus wall does not exist. This is mathematically modeled by increasing the value of the tip clearance to a large value, so that the effect of the image vortex is made negligible. Figure 3 compares the gust spectra at three spanwise locations for increasing values of tip clearance. The nondimensional tip clearance shown in Figure 2 is tip clearance divided by the forward rotor chord at the tip. Typical values of  $\tau$  for ducted fan rotors are  $\approx 0.01$ . It is seen that when  $\tau$  is increased by a factor of 1000, the solution has converged so that even an increase in  $\tau$  does not alter the results. For the sake of completeness, gust harmonic spectra for the case of no tip vortex (that is, wake alone) are also presented (Figure 3).

Although the tip vortex is seen to have considerable influence on the gust harmonic spectra at the tip streamline and at the streamline which is 89% of the span from hub; the gust harmonic spectra at the hub are not affected by the tip vortex. Also note that the gust spectral levels without the tip vortex (that is, wake alone) in the tip region are much lower in amplitude, compared to the hub region. This is because the smaller spacing and larger chord at the hub yield smaller values of streamwise distance/chord ratio which, in turn, makes the wakes stronger at the hub (compared to the tip).

The gust spectra (with the tip vortex) at the tip streamline and the streamline 89% of the span from hub demonstrate a different character. Based on the tip vortex trajectory model, the 89% streamline is very close to the region of impact of tip vortex on the aft rotor. (This aspect will be discussed further in Subsections 2.2 and 3.1.3). The gust spectral levels at the




Figure 3. Comparison of Gust Harmonic Spectra at Three Spanwise Locations for Increasing Values of Tip Clearance and for No Tip Vortex Case.

89% streamline are seen to be higher than for the tip streamline. The gust harmonic falloff for increasing values of the gust harmonic "q" is also lower for the 89% streamline (compared to the tip streamline), indicating a sharp profile for the gust waveform near the point of impact of the tip vortex.

#### 2.2 Empirical Relationships

As discussed in Subsection 2.1, computation of the flow field created due to the tip vortex can be performed if one knows both the:

- Circulation of tip vortex at the axial station of interest  $(\Gamma_{VIX})$
- Radial and tangential coordinates of the tip vortex (b<sub>r</sub> and b<sub>t</sub>).

The experimental data reported in Reference 8 contained information on the variation of (VF0)max and radius of the vortex core of a uniform NACA-0012 airfoil (with an aspect ratio of 6), set at an angle-of-attack of 7.5°, at two freestream velocities, 70- and 100-fps (feet per second). Vortex measurements were made with a yawhead pressure probe from 10 to 30 chord lengths downstream of the trailing edge. The experimental data chosen from Reference 7 were obtained on a NACA-0012 airfoil of an aspect ratio of 6 at a freestream velocity of 110-fps. The variation of tip vortex radius with angle-of-attack was measured at approximately six chord lengths downstream of the trailing edge using a vorticity meter. The applicability of the data (based on the wing configuration) to the significantly swept UDF®\* blade geometry should be verified once experimental tip vortex data can be obtained from these UDF® blade configurations.

Empirical corrections for  $(V_{\theta})$ max/ $(V_{\infty}\sqrt{C_L})$  and a/ $(c_{\infty}/C_L)$  were developed by employing a linear rational function of the type (Reference 3):

$$y = \frac{dx + e}{fx + 1} \tag{12}$$

where d, e, and f are empirically determined constants, and y could be  $(V_{\theta})$ max/ $(V = \sqrt{C_L})$  or a/ $(c \sqrt{C_L})$ , and x = s/c.

Constants d, e, and f in Equation 12 were determined through an iteration scheme aimed at minimizing the standard deviation (Reference 3 provides more details). The following correlations yielded minimum standard deviation:

$$\frac{(V_{\theta})_{\text{max}}}{V_{\infty} \sqrt{C_{L}}} = \frac{0.024 (s/c) + 0.5586}{0.0504 (s/c) + 1.0} = Y(s/c)$$
(13)

<sup>\*</sup> UDF & is a registered trademark of the General Electric Company, USA.

# OF POOR QUALITY

where:

 $(V_{\theta})_{max}$  = maximum tangential velocity of the tip vortex

 $V_{\infty}$  = freestream velocity

CL = local section lift coefficient

s = streamwise distance

c = chord

and

$$\frac{a}{c\sqrt{C_L}} = \frac{0.01584 (s/c) + 0.0014}{0.184 (s/c) + 1.0} = Z(s/c)$$
(14)

Figures 4 and 5 demonstrate these correlations, along with the data for:

$$\frac{(V_{\theta})_{\text{max}}}{V_{\infty}\sqrt{C_{L}}}$$
 and  $\frac{a}{c\sqrt{C_{L}}}$ ,

respectively. The empirical corrections provided in Equations 13 and 14 can be improved by adjusting the constants d, e, and f when more detailed experimental data for the UDF® blades become available.

By definition, the circulation of the tip vortex is:

$$(\Gamma)_{\text{vtx}} = \int_{\theta=0}^{2\pi} (V_{\theta})_{\text{max}} a d\theta$$

$$= \int_{\theta=0}^{2\pi} V_{\infty} \sqrt{C_{L}} Y(s/c) c \sqrt{C_{L}} Z(s/c) d\theta$$

$$= 2\pi (V_{\theta})_{\text{max}} a$$

$$= 2\pi (V_{\theta})_{\text{max}} a$$
(15)

Figure 6 shows the correlations given by Equations 13 and 14 and the computed circulation (Equation 15), along with the data. It is seen that the maximum tangential velocity decreases with s/c; whereas, the radius of the vortex core increases with s/c, and the tip vortex circulation initially rises and then shows almost no decay over 10 to 30 chord lengths. The absence of a decay in the circulation of the tip vortex noted in the above set of data has been confirmed on full-scale aircraft tip vortex measurements for up to 1,000 chord lengths downstream of the aircraft (Reference 15). The linear-rational-function correlations employed for  $(V_{\theta})_{\rm max}$  and




Figure 4. Correlation and Data for the Streamwise Variation of Normalized  $(V\theta)_{max}$  of the Tip Vortex.




Figure 5. Correlation and Data for the Streamwise Variation of Normalized Radius of the Tip Vortex Core.

#### ORIGINAL FACE IS OF POOR QUALITY

radius of the vortex core simulate this behavior of the tip vortex very well. Certain limiting forms of  $(\Gamma)_{vtx}$  are examined next. For example:

At 
$$(s/c) = 0$$
  $(\Gamma)_{vtx} = 2\pi V_{\infty} c C_L (0.5586 \times 0.0014)$  (16)

or

$$\frac{(\Gamma)_{\text{vtx}}}{2\pi \ V_{\infty} \ c} = 0.000782$$

For large values of s/c:

$$\lim_{(s/c) \to \infty} \left[ \frac{(\Gamma)_{\text{vtx}}}{2\pi \, V_{\infty} \, c \, C_{L}} \right] = \left( \frac{0.024}{0.0504} \right) \left( \frac{0.01584}{0.184} \right) = 0.040994$$
 (17)




Figure 6. Representative Correlation and Data for the Streamwise Variation of Normalized  $(V\theta)_{max}$ , Radius, and Circulation of the Tip Vortex.

Hence, for large values of s/c, the circulation of the vortex reaches an asymptotic value which is higher than the value at the trailing edge. The initial rise in tip vortex circulation (as indicated by these correlations) may be viewed as a result of the initial roll-up of the shed spanwise vorticity into a well-defined tip vortex. Thus, the correlations seem to represent some of the physical features exhibited by the wing tip vortices. Unfortunately however, for the UDF 80

configurations, the range of the s/c value (that is, spacing between the forward and aft rotors) is less than 5.0; within this range, there is a lack of data, as evidenced by Figures 4 through 6.

Flow-field visualization studies conducted on helicopter rotors (Reference 5) show that the shed tip vortices for rotating blade rows diffuse within one to two revolutions, and the distinction of the tip vortices is lost. However, no quantitative information exists regarding the circulation of  $(V\theta)_{max}$  or radius of such rotating tip vortices for use in modeling the decay of rotating tip vortices. The more rapid decay of rotating tip vortices (compared to translating tip vortices) may be due to the relatively larger turbulence and more efficient mixing processes prevalent in the near field of a rotating blade row, compared to a wing in translation wherein the decay could be due predominantly to viscous dissipation. In the absence of applicable information regarding the decay of the tip vortex for an unducted rotor, different power law decay rates are proposed for the current model:

$$(\Gamma)_{\text{vtx}} \propto \frac{1}{(1+s/c)^{\eta}} \tag{18}$$

Figure 7 demonstrates streamwise variations of normalized tip vortex circulation for three decay rates (that is,  $\eta = 0$ , 1/4, and 1/2); the exponential value that was used for tip vortices of the ducted fan rotor was 1/2 (Reference 3). The presence of the annulus wall and the large number of blades of a ducted fan rotor would cause a faster diffusion of tip vortex, compared




Figure 7. Streamwise Variation of Normalized Circulation of the Tip Vortex for Three Different Power Law Decay Rates.

to the unducted fan rotor; hence,  $\eta = 1/4$  is proposed as the exponent for the tip vortex decay rate of an unducted fan. The influence of the decay rate on the acoustic predictions of unducted rotors will be examined through parametric studies in Subsection 3.1.4.

Since the correlations for  $(V\theta)_{max}$  and radius of the tip vortex core (Equations 13 and 14) were developed using the data of wings of constant cross sections without any twist, the local section lift coefficient (CL) and chord distribution along the span did not vary; however, such is not the case for an unducted fan rotor. To determine what value of local section lift coefficient and chord must be used for computing  $(V\theta)_{max}$  and radius of the tip vortex core in this case, we resorted to published literature on helicopter tip vortices for some guidelines. The measurements and predictions of Donaldson, et al. (Reference 16) indicate that, for helicopter blades, the loading in only the outboard 30% span of the blade contributes to the tip vortex structure. The above criterion has been used as a guide in the selection of CL and "c" for the tip vortex of unducted rotors. Figure 8 shows the spanwise variation of local section lift coefficient for typical takeoff and cruise conditions for a typical unducted fan forward rotor blade design (such as, the F-7 blade). Figure 9 depicts the spanwise variation of chord for the F-7 blade. In accordance with Reference 16, the average values of lift coefficient and chord are computed using their distribution over the outboard 30% span. These average values, (CL)av and (c)av, are used as the parameters characterizing the tip vortex in computing  $(V_{\theta})_{max}$  and radius of the tip vortex core (Equations 13 and 14). This averaging procedure takes into account the spanwise variation of the blades and yields an "equivalent" blade of uniform section, in a very rough sense.

Due to a lack of detailed UDF® blade tip vortex experimental data, there is some uncertainty as to applicability of the value of  $(V\theta)_{max}$  and radius of the tip vortex core (see Equations 13 and 14), as these are based on the configuration of the wing, rather than of the UDF® blade. Therefore, an empirical factor known as the circulation index  $(C_i)$  was introduced to modulate the circulation of the tip vortex, which is defined as:

$$(\Gamma)_{VTX} = C_i \left\{ 2\pi \left( V_{\theta} \right)_{\text{max}} a \right\}$$

A value of  $C_i = 1$  reproduces the circulation given by Equation 15. The value of  $C_i > 1$  means that the tip vortex structure includes the influence of loading in more than the outboard 30% span of the blade. Conversely, the value of  $C_i < 1$  provides less circulation strength than is provided by Equation 15. Improvements to this simple procedure may be adopted when more information is available on characteristics of the tip vortices of the UDF\* blades. A sensitivity of the circulation index on the unsteady noise is studied and discussed in Subsection 3.1.1.

Next, an empirical relationship is developed for the trajectory of the tip vortices employing the flow visualization data (References 5 and 6) which were obtained for helicopter blades in a typical hover mode. All of these data indicated that tip vortices move radially inward for increasing axial distance, which is ascribable to the stream tube contraction (Figure 10).




Figure 8. Spanwise Variation of the Local Section Lift Coefficient for Takeoff and Cruise Conditions for F-7 Blades.




Figure 9. Spanwise Variation of the Chord for the F-7 Blade Design.




Figure 10. Correlation and Data for the Trajectory of the Tip Vortex.

Linear-rational-function correlation methods (Reference 3) were used again to develop an empirical relation for the trajectory of the tip vortex. Linear-rational functions are applicable if the dependent variable shows a monotonic trend with the independent variable. Since the radial movement of the tip vortex with axial distance is monotonic, approaching an asymptotic value, linear-rational function was chosen. The empirical relationship which yielded minimum standard deviation is:

$$\frac{R_{\text{vtx}}}{R_{\text{tip}}} = \frac{12 \ (Z_{\text{vtx}})/R_{\text{tip}} + 1.0}{16 \ (Z_{\text{vtx}})/R_{\text{tip}} + 1.0}$$
where

Rvtx: radial location of core of tip vortex

Z<sub>vtx</sub>: axial location of core of tip vortex.

Since the formulation for tip vortex discussed in Subsection 2.1 uses  $b_r = R_{tip} - R_{vtx}$ , Equation 20 is written in terms of b (see Figure 2 also):

$$\frac{b_{r}}{R_{tip}} = 1 - \frac{R_{vtx}}{R_{tip}} = \frac{4 (Z_{vtx})/R_{tip}}{16 (Z_{vtx})/R_{tip} + 1.0}$$
(21)

There is a lot of scatter in the data for large values of  $Z/R_{tip}$ ; this, mainly, is a result of the uncertainty in defining the tip vortex at large values of  $Z/R_{tip}$  due to the diffusion of the tip vortex.

The development of Equation 21 is based on the data base for helicopter rotors. The HTR for helicopter rotors is approximately less than 0.1; however, the HTR for the UDF® blades is approximately 0.4. This introduces some amount of uncertainty regarding the applicability of the tip vortex trajectory correlation of Equation 21 to the UDF® configuration. Due to the lack of a data base for the higher values of HTR, the general form of the tip vortex trajectory for UDF® blades is assumed from Equation 18 as follows:

$$\frac{b_{r}}{R_{tip}} = \frac{K_{vtx} (Z_{vtx})/R_{tip}}{16 (Z_{vtx})/R_{tip} + 1.0}$$
(22)

where K<sub>vtx</sub> is an adjustable constant.

For a given HTR, the tip vortex trajectory can be expressed in terms of a blade span percent of the tip by:  $(b_r/R_{tip})/(1\text{-HTR})$ . For example, the value of  $b_r/R_{tip} = 0.1$  translates to about a 17% span from the tip, with HTR = 0.4. On the other hand, the value of  $b_r/R_{tip} = 0.1$  approximates  $K_{vtx}$  to be 2 for  $Z_{vtx}/R_{tip} = 0.3$ . Thus, the value of  $K_{vtx}$  for the UDF® blades should be chosen with consideration of blade geometries, forward and aft rotor spacing, aeroperformance, etc., which would affect the tip vortex trajectories. The value of  $K_{vtx}$  was assumed to be between 0.5 and 2.0, based on a flow-field computation performed using GE's in-house codes. The parametric evaluation of the tip vortex trajectory on the unsteady noise due to the tip vortex is reported in Subsection 3.1.3. Again, a detailed experimental data base will be required to obtain the proper value of  $K_{vtx}$  for the UDF® blade configurations.

#### 3.0 Model Evaluation

The aerodynamic model for the tip vortex of counterrotating propulsors (described in Section 2.0) is evaluated in this section by:

- 1. Parametrically evaluating the effect certain key parameters (such as: tip vortex strength, drag coefficient, tip vortex trajectory, decay rate, tangential location of the tip vortex, and extent of clipping of the aft rotor) have on the acoustic characteristics of the counterrotating UDF® propulsors.
- 2. Comparing selective acoustic data and predictions of the counterrotating UDF® propulsors, aimed at evaluating the tip vortex model.

Due to the relatively low values of solidity over most of the span, UDF® propulsors may be viewed as isolated airfoils in computing the gust harmonic spectra resulting from impingement of the forward rotor wake and the tip vortex on the aft rotor. Hence, the unsteady gust model developed by Kemp and Sears (Reference 17) was selected for predicting the gust harmonic spectra of unsteady loadings induced by the tip vortex and the rotor wakes.

In the rotor wake model, the resultant aft rotor unsteady lift is strongly influenced by the forward rotor exit wake profile. As discussed in References 3 and 4, this wake profile modeling has been significantly affected by the drag coefficient of the local blade section. However, due to a lack of detailed UDF® aerodynamic data, there are large uncertainties to determine the accurate local section drag coefficient. The drag coefficients used in the present study were obtained based on GE's in-house analytical method, along with the aeroperformance of the scale model test of the UDF® configuration. The following section describes the sensitivity study of the drag coefficient on gust spectra and interaction noise levels.

#### 3.1 Parametric Studies

The studies described in this section parametrically evaluate the effect of certain geometric and aerodynamic parameters (described in Section 2.2) of the tip vortex on the acoustic characteristics of a counterrotating propeller. The principal objective of these studies was to develop an understanding of the sensitivity of the acoustic characteristics to certain key geometric and aerodynamic parameters of the tip vortex. The parametric studies described herein are:

- Influence of tip vortex strength and drag coefficient (C<sub>i</sub> and C<sub>d</sub>, respectively, sensitivity)
- Influence of tangential location of tip vortex (bt/s sensitivity)
- Influence of tip vortex trajectory (Kvtx sensitivity)
- Influence of decay rate of tip vortex (η sensitivity)
- Influence of progressive clipping of the aft rotor.

For the parametric studies, standard F-7/A-7 blade design parameters are used to calculate the gust harmonic spectra and unsteady loading noise through the present model; Figure 11 portrays a planform of these blades. The parametric studies are performed based on the aero-performance data of TP (test point) 3706 of a 90% rpm case with  $9 \times 8$  F-7/A-7 blades at a take-off Mach number, obtained from GE Cell 41. For an unequal blade number configuration (such as,  $9 \times 8$ ) but equal rpm, the steady loading and thickness noise and the noise due to wake/tip vortex interaction occur at distinctly different frequencies (Reference 11), as listed below:

Steady loading and thickness noise of forward rotor

$$f_{siq} = q * \frac{rpm1}{60} * B1 q = 1, 2, 3, ...$$
 (23)

where  $f_{s1q}$  is the  $q^{th}$  harmonic of steady loading and thickness noise of the forward rotor, and B1 is the number of blades in the forward rotor, and q = 1 corresponds to BPF (blade passing frequency), q = 2 corresponds to  $2 \times BPF$  of forward rotor, etc.






Figure 11. Planform of the F-7/A-7 Unducted Fan Blade Design, Showing the Extent of Clipping on the Aft Rotor.

Steady loading and thickness noise of aft rotor

$$f_{s2r} = r * \frac{rpm2}{60} * B2 r = 1, 2, 3 ...$$
 (24)





where  $f_{s2r}$  is the  $r^{th}$  harmonic of steady loading and thickness noise of the aft rotor; B2 is the number of blades in the aft rotor; and r = 1 corresponds to BPF; r = 2 corresponds to  $2 \times BPF$  of the aft rotor, and so on.

• Noise due to wake/tip vortex interaction

$$f_{wqr} = f_{s1q} + f_{s2r}, r = 1, 2, 3 ...$$
 (25)

For equal rpm's (say, rpm1 = rpm2 = rpm), normalized frequencies are defined as:

$$\bar{f}_{slq} = \frac{f_{slq}}{(rpm/60)} = qB1, q = 1, 2, 3 ...$$
(26)

$$\bar{f} = \frac{f_{2sr}}{(rpm/60)} = rB2, r = 1, 2, 3 ...$$
 (27)

and

$$\bar{f}_{wqr} = \frac{f_{wqr}}{(rpm/60)} = qB1 + rB2, \quad q = 1, 2, 3, \dots r = 1, 2, 3, \dots$$
 (28)

The spinning mode numbers associated with steady loading and thickness noise of forward and aft rotors are qB1 and rB2, respectively. The spinning mode number associated with the noise due to wake/tip vortex interaction is given by:

$$m_{\text{wqr}} = rB2 - qB1 \tag{29}$$

where m<sub>wqr</sub> is the spinning mode number of the rth harmonic or aft rotor unsteady noise, due to qth gust harmonic of forward rotor.

Table 1 lists the tone designation,  $f_{wqr}$ ,  $m_{wqr}$ , q, and r for increasing frequencies for a  $9 \times 8$  blade configuration. Figure 12 is a schematic of the steady loading and unsteady loading noise spectra for the  $9 \times 8$  blade number configuration.

In the following parametric studies, the sensitivity of each parameter was examined individually by varying the particular parameters from the basic stage of each. The value of each parameter at the basic stage is given as  $C_i = 2.0$ ,  $K_{vtx} = 2.0$ , bt/S = 0.5, and  $\eta = 1/4$ .

### 3.1.1 Influence of Tip Vortex Strength and Drag Coefficient

Gust spectra and consequential interaction noise levels are affected by both rotor viscous wake and tip vortex flow field. In the present work effort, the viscous wake and the tip vortex flow fields are modeled independently and are then summed to obtain total unsteady gust loadings on the aft rotor. When the unsteady loading is dominated by the viscous rotor wakes, the tip vortex effect becomes small, and vice versa. The sensitivity of the strength of the viscous wake and the tip vortex on gust spectra and interaction noise levels is studied by parametrically

Table 1. Normalized Acoustic Frequencies and Spinning Modes Associated with Wake/Tip Vortex Interaction for a 9×8 Blade Number Configuration.

Tone	-			
Designation	$f_{\mathbf{wqr}}$	$m_{wqr}$	q	r
(A + F)	17	-1	1	1
(2A + F)	25	7	1	2
(A+2F)	26	-10	2	1
(3A + F)	33	15	1	3
(2A + 2F)	34	-2	2	2
(A+3F)	35	-19	3	1
(4A + F)	41	23	1	4
(3A+2F)	42	6	2	3
(2A+3F)	43	-11	3	2
(A+4F)	44	-28	4	1
(5A + F)	49	31	1	5
(4A + 2F)	50	14	2	4
(3A+3F)	51	-3	3	3
(2A+4F)	52	-20	4	2
(A+5F)	53	-37	5	1

fwgr - Normalized acoustic frequency

mwqr - Spinning mode

q - Forward rotor gust harmonic

r - Aft rotor acoustic harmonic




Figure 12. Schematic of a Narrowband Acoustic Spectrum of a 9 + 8 Blade Number Configuration.


### ORIGINAL PAGE IS OF POOR QUALITY


varying the circulation index of the tip vortex model and the drag coefficient (Cd) of the rotor viscous wake model.

The influence of the circulation of the tip vortex on gust spectra and its consequential sensitivity on the interaction noise is shown in Figure 13 where the parametrically varying Ci has a fixed value of  $K_{VIX} = 2.0$  and bt/s = 0.5. A "no tip" vortex is also included, for the sake of completeness. Figure 13 presents the predicted sensitivity of the circulation index on gust harmonic spectra at the tip streamline with three different values of Cd (0.03, 0.02, and 0.005); similarly, Figures 14 and 15 illustrate the Ci effect for these values of Cd at the streamlines of 70.7% and 45.4% span from the hub, respectively.

At the tip region (Figure 13), gust harmonic spectra for each C<sub>i</sub> value have similar levels (regardless of C<sub>d</sub>), even though the viscous wake gust spectra denoted by no tip are quite different from the nonzero C<sub>i</sub> cases. The difference between no tip and nonzero C<sub>i</sub> is the effect of the tip vortex. As demonstrated in Figure 15, the gust harmonics collapse into one line at the location far away from the tip vortex center where the tip vortex effect is minimal.

As shown in Figure 14, at the 70.7% span location from the hub, the spectra with  $C_d = 0.03$  and 0.02 exhibit small spread, due to the different  $C_i$  values for the lower gust harmonics (q = 1, 2, 3, and 4); but the spectra with  $C_d = 0.005$  shows a relatively large spread for three  $C_i$  values. This indicates that the sensitivity of tip vortex strength on the gust harmonics depends on the levels of drag








Figure 13. Predicted Effect of Tip Vortex Strength on Gust Harmonic Spectra with Three Different Ca Values at the Streamline of 100% Span from the Hub.




Figure 14. Predicted Effect of the Tip Vortex Strength on Gust Harmonic Spectra with Three Different C<sub>d</sub> Values at the Streamline of 70.7% Span from the Hub.




Figure 15. The Predicted Effect of Tip Vortex Strength on Gust Harmonic Spectra with Three Different C<sub>d</sub> Values at the Streamline Location of 45.4% Span from the Hub.

coefficient. The effect of the tip vortex becomes minimal at the streamline of 45.4% span from the hub (Figure 15).

Figure 16 illustrates the predicted effect of the tip vortex strength (Ci) on the interaction tone SPL (sound pressure level) sum with  $C_d = 0.005$ . Since the value of Cd is small, the circulation index sensitivity is clearly shown as 4 to 6 dB; however, the directivity of SPL sum was preserved for the various Ci values. To examine the predicted effect of the drag coefficient on the interaction tone SPL sum with a fixed value of  $C_i = 2.0$ , Figure 17 is given for  $C_d = 0.03, 0.02, \text{ and } 0.005.$  Although the drag coefficient effect is seen at the forward arc of the emission angle, the Cd effect becomes negligible at the aft rotor. Thus, prediction of the averaged acoustic quantities of PNL, PNLT, or EPNL would be significantly influenced by the SPL sum directivity.

Figure 18 provides a summary of the predicted tip vortex effect for the C<sub>d</sub> values of 0.03, 0.02, and 0.005 on the interaction tone sum directivity by comparing the SPL sum predictions, both with and without the tip vortex. The interaction tone sum directivity is computed both with and without the tip vortex model turned on. The differences between these two SPL directivities indicate the isolated tip vortex effect, since both cases contain the interaction tones induced by the rotor viscous wakes. As presented in Figures 13 through 15, the tip vortex effect becomes significant as the values of Cd are reduced. It should be emphasized that the accurate acoustic predictions, using the current model, depend upon

#### ORIGINAL PAGE IS OF POOR QUALITY




Figure 16. The Predicted Effect of the Tip Vortex Strength on Interaction Tone SPL Sum with  $C_{\rm d}\,=\,0.005$ .




Figure 17. Predicted Effect of the Drag Coefficients on the Interaction Tone SPL Sum with  $C_1 = 2.0$ .

# ORIGINAL PAGE IS OF POOR QUALITY




Figure 18. Predicted Tip Vortex Effect of the Drag Coefficients (0.03, 0.02, and 0.005) on Interaction Tone SPL Sum with  $C_{\rm c}=2.0$ .

the accuracy of the section local drag coefficients and the tip vortex strength (which are not available at the present time, due to the lack of experimental data).

#### 3.1.2 Influence of Tangential Location of Tip Vortex

The tangential position of the tip vortex, relative to the wake centerline, is a critical parameter in determining the gust waveform shape and amplitude. Figure 19 compares the gust waveform shape for four values of tangential position of the tip vortex at three radial locations. The gust waveform shape for the case of wake alone (that is, no tip vortex) is included for the sake of completeness. The wake flow field is assumed to be symmetrical on either side of the blade (pressure or suction). Even though this assumption may not be valid, applicable data to model the asymmetry of the wake are lacking. Thus, the gust wave shape for  $0.5 \le x/S \le 1.0$  is a mirror image of the gust waveform shape over  $0.0 \le x/S \le 0.5$  without the tip vortex; however with tip vortex, a wavelength of the gust waveform shape becomes equal to blade-to-blade spacing and is not symmetrical between  $0.0 \le x/S \le 0.5$  and  $0.5 \le x/S \le 1.0$ .

The gust velocity at the tip streamline and at 70.7% span from hub streamline are quite small for cases without the tip vortex effect, as compared to those cases with the tip vortex effect. At the hub streamline, this model predicts no tip vortex influence on the gust velocity. For bt/S = 0.0 (where tip vortex is located at the wake centerline), the upwash velocities at the tip and 70.7% streamlines shoot up at x/S = 0.0. For bt/S = 0.25, the presence of the tip vortex is indicated by the large increase at x/S = 0.25 at the tip and 70.7% streamlines; similarly for bt/S = 0.33, significant tip vortex influence is shown at x/S = 0.33. For bt/S = 0.5, the gust velocity shape is altered significantly (it is a downwash instead of an upwash, as was the case for other bt/S values).

Figure 20 shows the Fourier decomposition of the gust waveforms depicted in Figure 19 to yield the gust harmonic spectra. For bt/S = 0.5, the even-numbered gust harmonics are higher in amplitude (than the odd-numbered gust harmonics), due to two similar dips within one passage; one due to wake, and one due to the tip vortex. For bt/S = 0.25, the dips/hills due to tip vortex interact with the wake, and the resulting waveform is not symmetric (as was bt/S = 0.5) which causes higher gust spectral values for odd-numbered gust harmonics. Similar behavior can be seen from bt/S = 0.33. When bt/S = 0.0, the dips/hills due to wake and tip vortex yield a sharp gust profile at the wake centerline (similar to an impulse function). This results in high values for all gust harmonics. At the hub streamline, there is no tip vortex influence.

Next, the influence of the tangential location of tip vortex on interaction noise is considered, based on the case demonstrated in Figures 19 and 20. Figure 21 compares the predicted and measured interaction noise tones; that is, 1A + 1F through 2A + 3F tones at an observer angle of  $131^{\circ}$  for bt/S = 0.5, 0.33, 0.25, and 0.0. The measured data were obtained from the GE Cell 41 data base. It is apparent that the tangential location of tip vortex strongly affects the 1A + 2F and 2A + 2F tones; for example, a 10-dB spread (depending on the values of bt/S). However, the sensitivity of the bt/S value on the other interaction tones is relatively small (less than 5 dB). However, Figure 10 reveals large underpredictions of the model on 1A + 2F and




Figure 19. Predicted Tangential Distribution of Gust Velocity at Three Radial Locations for Various Tangential Locations of Tip Vortex, and for the Case of No Tip Vortex.




Figure 20. Predicted Effect of Tangential Location of Tip Vortex on Gust Harmonic Spectra at Three Radial Locations.

1A+3F tones regardless of the value of bt/S. This indicates that further improvement and modification are needed on the model. Since values of bt/S depend on blade configurations and aeroperformance, it is difficult to determine the optimal value of bt/S without a detailed rotor aerodynamics data base at the present time.




Figure 21. A Comparison of the Predicted and Measured Individual Interaction Tones.

Figure 22 depicts the sensitivity of tone SPL sum of interaction noise directivity to the tangential location of the tip vortex. The sum of interaction tones is not influenced by the different values of bt/S, up to the emission angle of 120°. The predictions of the SPL sum agree relatively well with the measured data (accurate within 2 to 5 dB), even though each individual tone prediction was not so good (Figure 21). Figure 22 indicates that the tangential location of the tip vortex has no significant impact on the interaction tone SPL sum. The value of bt/S = 0.5 has been used in this report.

## 3.1.3 Influence of Tip Vortex Trajectory

The influence of the tip vortex trajectory on gust spectra and its consequent influence on the interaction noise were studied by parametrically varying the  $K_{vtx}$  (see Equation 22).




Figure 22. Sensitivity of the Tone SPL Sum of Interaction Noise to the Tangential Location of Tip Vortex.

Figure 23 indicates the predicted influence of the tip vortex trajectory on the gust harmonic spectra at three streamlines in the tip region. As  $K_{VIX}$  increases, the tip vortex moves radially inward. At the tip streamline, the gust harmonic spectrum for  $K_{VIX}=0.5$  has the highest levels (compared to  $K_{VIX}=1$  and 2), since the tip vortex for  $K_{VIX}=0.5$  is closest to the tip streamline. For the 89.1% streamline, the gust harmonic spectrum for  $K_{VIX}=1$  has the highest levels compared to  $K_{VIX}=0.5$  and 2, since the 89.1% streamline is closer to the tip vortex point of impact when  $K_{VIX}=1$ . However, for the 70.1% streamline, gust spectrum levels for  $K_{VIX}=0.5$  and 1 are about same. This indicates the tip vortex effects induced by  $K_{VIX}=0.5$  and 1 are minor at this streamline location. The gust spectrum levels for  $K_{VIX}=2$  are quite different from others. The noted relative dominance of even-numbered gust harmonics over odd-numbered gust harmonics is due to the fact that the tangential location of the tip vortex is at the midpassage.

Figure 24 shows the influence of the tip vortex trajectory on each individual interaction tone at an observer angle of 91° along with the data. Apparently, the sensitivity of  $K_{vtx}$  on the acoustic predictions is insignificant. This probably happens because the gust spectra at different radial locations are enhanced for different values of  $K_{vtx}$ . The comparisons between data and predictions indicate that the  $K_{vtx}$  values do not improve the accuracy of the model. The differences between the predictions and data (up to 10 dB) are noted in Figure 24.

# ORIGINAL PAGE IS OF POOR QUALITY




Figure 23. Predicted Influence of the Tip Vortex—Trajectory on Gust Harmonic Spectra at Three Streamlines in the Tip Region.




Figure 24. Predicted Influence of Tip Vortex Trajectory on Each Interaction Tone at Observer Angle of 91°.

Figure 25 shows the influence of tip vortex trajectory on the directivity of tone SPL sum of interaction noise. Variations in the tip vortex trajectory do not significantly alter the interaction tone SPL sum; however, the trajectory parameter does significantly affect the interaction noise prediction for the clipped aft rotor blades configuration, as shown in Subsection 3.1.5.




Figure 25. Predicted Influence of Tip Vortex Trajectory on Interaction Noise Tone SPL Sum.

### 3.1.4 Influence of Decay Rate of Tip Vortex

Also investigated was the influence of the decay rate of the tip vortex on gust harmonics and, thus, on the noise. As discussed in Section 2.2, a power law decay rate was proposed for the circulation of the tip vortex:

$$(\Gamma)_{\text{vtx}} \propto \frac{1}{(1 + s/c)^{\eta}} \tag{18}$$

The cycle corresponds to a typical cutback. Figure 26 demonstrates the predicted gust harmonic spectra for tip vortex decaying with different rates at the streamlines of the tip and 70.7% span from the hub. The case of no tip vortices also was included for the sake of comparison. For this study,  $K_{vtx} = 2.0$  and bt/S = 0.5 are used.

The gust spectral levels for the nondecaying tip vortex are the highest. As the rate of decay increases from 0 to 1/4, to 1/2, the gust spectral levels decrease monotonically.

# 3.1.5 Influence of Progressive Clipping of Aft Rotor

As discussed in Subsection 3.1.1, the tip vortex is obviously a noise-generating mechanism. Thus, by clipping the aft rotor to minimize interactions between the tip vortex and the aft rotor blades, the interaction noise is reduced. This phenomenon has also been verified from the GE in-house UDF® acoustic data base. The thrust loss due to clipping and the associated required reduction in shp (shaft horsepower) can be made up either by increasing the rpm, or loading of the aft rotor; however in this parametric study, no attempt has been made to recover thrust loss resulting from clipping. This study was conducted with the objective of discovering the sensitivity (relating to the percent clipping of the aft rotor) on noise reductions. Consequently, this study considered four values of percent span clipping (5%, 10%, 15%, and 20%), in addition to 0% and 25% span clippings. Figure 11 presented the planforms of the standard F-7/A-7 and the F-7/A-7 with 25% clipping of span on the aft rotor.

Thrust and shp data are available only at 0% and 25% clippings for  $M_{\infty} = 0.25$ . Figure 27 shows the assumed interpolation of the thrust and shp of the aft rotor with the end points (0% and 25% clipping) coinciding with data for the 90% rpm case.

The steady loading and thickness noise and the wake/tip vortex interaction noise occur at distinctly different frequencies for unequal blade number configurations (Figure 12). As illustrated in Figure 12, tones associated with the steady loading and thickness noise were summed on a mean-squared pressure basis; this is also true for the tones associated with the wake/tip vortex interaction noise. Figure 28 demonstrates the predicted effect of progressive clipping of the aft rotor on the sum of steady loading and thickness noise. It is evident that the steady loading and thickness noise reduces uniformly as the percent clipping increases, a reflection of the assumed performance of clipped aft rotor (Figure 27). Predicted effect of the clipping




Figure 26. Predicted Gust Harmonic Spectra at Two Rotor-to-Rotor Spacings for the Tip Vortex at Different Decaying Rates and for the Case of No Tip Vortex at Two Streamline Locations.




Figure 27. Assumed Performance of the Progressively Clipped Aft Rotor.




Figure 28. Predicted Effect of Progressive Clipping of the Aft Rotor on the Steady Loading and Thickness Noise.

sensitivity on the interaction tones is portrayed in Figure 29; whereas, the predicted effect on the OASPL (overall sound pressure level) is presented in Figure 30.

As discussed previously, unsteady loading interaction tone predictions depend on many empirical correction parameters. To predict the clipping effect on the interaction noise, the tip vortex strength (C<sub>i</sub>) and the tip vortex tangential location (bt/S) were fixed at 2.0 and 0.5, respectively. Figure 29 (View A) shows the predicted effect of progressive clipping of the aft rotor on wake/tip vortex interaction noise by using  $C_d = 0.02$  and  $K_{vtx} = 2.0$ . As previously stated (Subsection 3.1.1), the value of  $C_d = 0.02$  induces the strong rotor viscous wakes which control the interaction noise generation and reduces the influence of the tip vortex. Since the tip vortex effect is small with a combination of these C<sub>d</sub> and K<sub>vtx</sub>, the clipping effect is also shown as small ( $C_d = 0.02$ ).

On the other hand, View B of Figure 29 shows the significant clipping effect when the drag coefficient is reduced to 0.005 to amplify the effect of the tip vortex. With the value of  $K_{VIX} = 2.0$ , the tip vortex is located approximately at 17% span from the tip of the aft rotor; thus, a large reduction in interaction noise is obtained by going from 15% to 20% clipping, and there are no reductions for percent clippings less than 15% span, as evidenced in Figure 29, View B.

The predicted clipping effect with  $C_d = 0.005$  and  $K_{vtx} = 1.0$  is depicted




Figure 29. Predicted Effect of Progressive Clipping of the Aft Rotor on the Wake/Tip Vortex Interaction Noise.




Figure 30. The Predicted Effect of Progressive Clipping of the Aft Rotor on the OASPL Directivity.

in Figure 29 (View C), where the only difference between Views B and C is the reduction of  $K_{vtx}$  (from 2.0 to 1.0). With  $K_{vtx} = 1.0$ , the tip vortex center is located at about 8% span; thus, a significant noise reduction is observed with the 10% and 15% clippings. Hardly any noise reduction is noted for clippings less than 5% or greater than 20%, since the influence of the tip vortex is concentrated at approximately 8% span.

Figure 30 (Views A through C) reveals predicted OASPL directivities for the various percent clippings with values of Cd and Kvtx corresponding to those used in Figure 29 (Views A through C, respectively). The OASPL reduction due to the aft rotor clipping is clearly shown, but the magnitudes of reduction are not as significant as those of the interaction noise. This is primarily due to the relatively high levels of the aft rotor steady loading and thickness noise.

This study has demonstrated that the current tip vortex model can be used to predict the interaction noise reduction that can be attained by the clipping of the aft rotor. However, to determine the optimum value for percent clipping of the aft rotor, in terms of noise reductions at a nominal thrust loss, the empirical correction parameters of the current model need more refinements. This effort is currently in progress as part of a GE IR&D project.

#### 3.2 Data - Predictions Evaluation

Systematic data/theory comparisons are performed to evaluate the applicability and limitations of the current tip vortex model. Figure 11 provided a planform of the standard F-7/A-7 blade design, along with the clipped aft rotor. Narrowband acoustic data, measured at Cell 41 for the F-7/A-7 (standard and clipped) blade geometries at a freejet Mach number of 0.25 and an axial distance of 0.2408 between pitch-change axes angle, were used to perform the following comparisons of data and theory. The acoustic data have been transformed from the freejet situation to an equivalent flight situation by accounting for the refraction effect of the freejet shear layer using ray theory, in order that a one-to-one comparison of data and theory can be performed. These comparisons, as discussed below, refer to a 90% rpm case (Test Points 3706 and 4110). Test Point 3706 is for the standard A-7 blade, and Test Point 4110 is for the clipped A-7 blade. For Test Point 4110, the aft pitch angle was opened to recover the thrust loss due to clipping, but the rpm was maintained to be the same for both standard and clipped configurations. Figure 31 identifies the shp and pitch angle data. The narrowband data employed has a bandwidth from 6 Hz to 5 kHz. Since the BPF is at about 1 kHz, the narrowband data contains tones up to about 5 harmonics of BPF.

Figure 31 compares measured and predicted directivities of the tone SPL sum of all of the steady loading and thickness noise for standard and clipped aft rotor blades. The tone SPL sum was obtained by adding only the tones associated with the steady loading and thickness noise of the forward and aft rotors on a mean-squared pressure basis. The measured reduction in steady loading noise due to the clipping of the aft rotor is well predicted; the directivities also are in relatively good agreement. Figure 32 compares the measured and predicted steady loading and thickness tones for standard and clipped aft rotor at an observer angle of 105°. The measured and predicted reductions in tone levels of the aft rotor BPF and its harmonics, indicated by 1A and 2A, due to clipping are in good agreement. The measured and predicted tone levels of the forward rotor BPF and its harmonics (denoted by 1F, 2F, and 3F) are also in good agreement. Actual tone data reveal a slower falloff with an increase in harmonics, as compared to the predictions; this may indicate the presence of some inflow distortion into the rotors.

Figures 33 through 36 compare the predicted and measured tone SPL sum for wake/tip vortex interaction noise for unclipped and clipped aft rotor cases. As previously discussed, the interaction tone predictions are sensitive to the empirical constants utilized in the tip vortex model. Therefore, several sets of the empirical constants are tested in the following data/theory comparisons and are specified in each figure. The term "no tip vortex" in the figures indicates that the tip vortex model was turned off for the specific predictions and that, these interaction tones are induced only by the forward rotor viscous wakes. The tone SPL sum was obtained (as in the case of steady loading and thickness noise) by adding all of the interaction noise tones on a mean-squared pressure basis.

The predictions presented in Figure 33 were performed using the empirical constants of  $C_d = 0.02$ ,  $C_i = 2$ ,  $K_{vtx} = 2.0$ , and bt/S = 0.5 for the tip vortex model. As discussed, the value of  $C_d = 0.02$  produces such strong viscous wakes that the tip vortex effect is masked. However,

# ORIGINAL PACE OF POOR QUALITY




Figure 31. Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Steady Loading and Thickness Noise.





Figure 32. Comparison of the Measured and Predicted Steady Loading and Thickness Tones for Standard and Clipped Aft Rotor at 105° Observer Angle.







Figure 33. Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Interaction Tone SPL Sum With andWithout the Tip Vortex Model ( $C_{\rm d}=0.02,\,C_{\rm i}=2,\,K_{\rm vix}=2.0,\,bvS=0.5$ ).







Figure 34. Comparison of the Effect (Measured and Predicted) of Clipping of the Aft Rotor on Interaction Tone SPL Sum With andWithout the Tip Vortex Model ( $C_{\rm d}=0.005,\,C_{\rm f}=2,\,K_{\rm vtx}=2.0,\,bt/S=0.5$ ).



100

By

90

D 0% Data
D 25% Data
D 25% Data
A 0% Prediction
+ 25% Prediction

80

70

90

110

130

150

Emission Angle

Figure 35. A Comparison of the Measured and Predicted Effect of the Clipping of the Aft Rotor on Interaction Tone Sum With and Without the Tip Vortex Model ( $C_{\rm d}=0.005,\,C_{\rm f}=1,\,K_{\rm vtx}=2.0,\,bt/S=0.5$ ).




Figure 36. A Measured and Predicted Effect Comparison of Clipping of the Aft Rotor on Interaction Tone Sum With andWithout the Tip Vortex Model ( $C_{\rm d}=0.005, C_{\rm i}=3, K_{\rm vtx}=2.0, bt/S=0.5$ ).

the predictions with no tip vortex indicate that the clipping blade increases the interaction tone sum, which contradicts the data. The predictions in Figure 34 are performed with a  $C_d$  of 0.005; results indicate the accurate predictions of the clipping effect, but with the underpredictions of the SPL. Without the tip vortex model, Figure 34 shows that predictions for both the standard and clipped blades are underpredicted and that, the interaction tone noise is still higher for the clipped case than for the standard case. The Figure 35 predictions are performed with the same empirical parameters as in Figure 34, except that the tip vortex value is reduced from 2.0 to 1.0, in order to locate the tip vortex center closer to the tip of the standard blade. As a result, the prediction for the standard blade agrees relatively well with the data, but the clipped blade is still underpredicted. Finally, Figure 36 presents the predictions made with the same empirical constants used in Figure 35, except  $C_i$  is increased to 3.0. With this set of parameters, the data/theory comparisons show good predictions for the standard aft blade configuration; however, the inaccurate prediction of the clipped blades was still present. Since predictions with no tip vortex are not affected by the  $K_{VtX}$  and  $C_i$  values, the no tip vortex comparisons in Figures 34 through 36 are identical to each other.

Next, data and theory comparisons of the individual interaction tone directivity contained within the interaction tone sum of Figure 36 are examined utilizing the empirical constants of  $C_d = 0.005$ ,  $C_i = 3$ ,  $K_{vtx} = 1$  and bt/S = 0.5. Figure 37 compares predicted and actual data for 1A + 1F, 2A + 1F, 1A + 3F, 2A + 2F and 3A + 1F interaction tones (Table 1 identifies these interaction tones), both with and without the tip vortex model. For each interaction tone, the predicted  $\Delta dB$  between standard and clipped aft rotors is in better agreement with the data for cases with tip vortex influence, as compared to those without tip vortex. Note that predictions for the clipped aft rotor (with or without the tip vortex model) have altered only slightly. However for most individual interaction tones, the predictions for the standard aft rotor with the tip vortex model have increased, relative to those without the tip vortex model. In general, it is obvious that the current acoustic prediction model including viscous wake/tip vortex model can not predict accurate individual interaction tones, even though (as demonstrated in Figures 33 through 36) the interaction tone sum can be well-predicted.

To examine the effect of the rotor viscous wake alone, Figure 38 demonstrates the predicted spanwise variation of the streamwise distance per chord, normalized wake centerline defect, and the semiwake width for Test Point 3706, with the C<sub>d</sub> values of 0.02 and 0.005. This figure does not contain the tip vortex effect. It is seen that due to relatively large s/c values in the tip region, the wake has decayed much more (compared to the hub region). The semiwake width determines the shape of the gust harmonic spectra, and the wake centerline defect determines the amplitude of the gust spectra (Reference 3). The harmonic falloff rate increases as the semiwake width increases. The amplitude of the gust spectra increases with a corresponding increase in the wake centerline defect. Due to the deeper (larger values of the wake centerline defect) and the narrower (smaller values of semiwake width) wakes in the hub region, compared to the tip region, the gust harmonic levels that are due to wake alone are much higher in the hub region tham in the tip region. Therefore, the contribution of the wakes from the outer 25% span in the tip region probably is not a significant contribution to the total interaction noise. Accordingly, the outer 25% span of the aft rotor was clipped; the total interaction




Figure 37. Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Individual Interaction Tones, With and Without the Tip Vortex Model ( $C_{\rm d}=0.005,\,C_{\rm t}=3,\,K_{\rm vtx}=1.0,\,bt/S=0.5$ ).




Figure 37. Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Individual Interaction Tones, With and Without the Tip Vortex Model ( $C_{\rm d}=0.005, C_{\rm t}=3, K_{\rm MX}=1.0, bt/S=0.5$ ), Concluded.




Figure 38.—The Predicted Spanwise Variation of Normalized Streamwise Distance, Wake Centerline Defect, and Semiwake Width.

noise is not predicted to be much different from the standard blade case (for the wake alone model).

A set of data and theory comparisons also were generated for 80% rpm for standard (Test Point 3704) and clipped (Test Point 4104) aft rotor blades. Aeroperformance data for these two test points are contained in Figure 39, where the pitch angle of the clipped aft rotor is opened more (than that of the standard aft rotor) to recover performance loss caused by the clipping. Figure 39 compares the measured and predicted directivities of the tone SPL sum of steady loading and thickness noise for standard and clipped aft rotor configurations. As in the case of 90% rpm (Figure 31), the predicted reduction in steady loading and thickness noise due to clipping of the aft rotor is in relatively good agreement with the data.

Figure 40 compares measured and predicted effects of clipping of the aft rotor on interaction tone SPL sum, with and without tip vortex model. The predictions are performed with the empirical constants of  $C_d=0.005$ ,  $C_i=3$ ,  $K_{vtx}=1$ , bt/S=0.5, as in Figure 36 of the 90% rpm case. As in the case of 90% rpm (Figures 33 through 36), when the tip vortex model is included in the predictions, the predicted  $\Delta dB$  between standard and clipped aft rotor is in better agreement with the data, as compared to those where the tip vortex model is not included. The predicted  $\Delta dB$  with the tip vortex model between standard and clipped aft rotor, however, is greater than the measured  $\Delta dB$ . Since the  $C_i$  (or strength) of the tip vortex is computed based on the average lift coefficient over the outboard 30% of the span in the current model (Section 2.2), the strength of the tip vortex is reduced at lower rpm; hence, the prediction at 80% rpm (due to clipping) is seen as lower than that predicted at 90% rpm. The measured  $\Delta dB$  due to clipping at 80% rpm is seen as greater than that at 90% rpm (Figures 36 and 40). Hence, the predicted change (with the tip vortex model) of the effect of clipping with rpm contradicts other data with this particular set of empirical constants.

Figure 41 summarizes the comparisons for the measured and predicted effect of clipping of the aft rotor on 1A + 1F, 2A + 1F, 1A + 2F, 3A + 1F, 2A + 2F, and 1A + 3F interaction tones at 80% rpm, with and without tip vortex. Figure 41 indicates that predictions for the standard aft blade are in relatively good agreement with the data using the tip vortex model, although data/theory comparisons for the clipped blade need improvement. In general, the predicted  $\Delta dB$  (due to clipping of the aft rotor) when the tip vortex model is included is still in better agreement with the data, as compared to those predictions not including the tip vortex model.

These comparisons of data and theory show that the current model can be utilized to investigate the noise characteristics of the UDF® blade configuration and can, eventually, become a useful design tool when the empirical constants used in the present model will be determined accurately from well-controlled experimental studies.




Figure 39. Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Steady Loading and Thickness Noise for 80% rpm.




Figure 40. Measured and Predicted Effect of Clipping of the Aft Rotor on Interaction Tone SPL Sum With andWithout the Tip Vortex Model ( $C_{\rm d}=0.005,\,C_{\rm f}=3,\,K_{\rm MX}=1.0,\,{\rm bt/S}=0.5$ ).




Figure 41. Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Individual Interaction Tones, With and Without the Tip Vortex Model ( $C_{\rm d}=0.005, C_{\rm f}=3, K_{vtx}=1, bt/S=0.5$ ).




Figure 41. Comparison of the Measured and Predicted Effect of Clipping of the Aft Rotor on Individual Interaction Tones, With and Without the Tip Vortex Model ( $C_{\rm d}=0.005, C_{\rm t}=3, K_{\rm vtx}=1, bt/S=0.5$ ), Concluded.

#### 4.0 Conclusions and Recommendations

This report has documented the analytical modeling, limited data and model prediction comparisons, and certain key parametric studies pertaining to the tip vortex as a part of the noise-source mechanism for unsteady loading noise of counterrotating propellers. The viscous rotor wake effect is also modeled in order to compute the unsteady loading noise. The upwash field created by the combined tip vortex and the viscous rotor wake was analytically modeled employing an approach previously taken for fan tone noise. The strength, size, and streamwise development of the tip vortex are empirically modeled, based on fixed wing and helicopter rotor data. The present work should be considered as a basic frame model containing a number of empirical constants. These constants cannot be defined accurately at the present time, due to insufficient aerodynamics data for the UDF® blades configurations. However, the model has been structured in such a manner that it can be improved and refined with minor modifications when detailed UDF® aerodynamics data become available. Some of the significant conclusions and recommendations for future work are presented in the following sections.

#### 4.1 Conclusions

The following significant conclusions are a product of the above-described analyses:

- The measured reduction in interaction noise due to clipping of the aft rotor is very well predicted by the tip vortex model; however, the wake-alone model (that is, without the tip vortex) could not predict the measured reduction in interaction noise due to clipping.
- The tangential location of tip vortex affects the gust harmonic spectra which, in turn, has a relatively small bearing on the interaction noise (an average of 5 dB). The influence of the bt/S value on the interaction tones sum predictions is minor.
- Tip vortex trajectory does not have a noticeable impact on the interaction noise for the standard aft blade configuration; however, it controls the effectiveness of the clipping on interaction noise levels for the clipped aft blade configuration.
- The decay rate of the tip vortex has a very significant effect on the noise reduction achievable due to an increase in rotor-to-rotor spacing.
- The section local drag coefficient and the tip vortex strength interact with each other and have a strong influence on the interaction tones.

#### 4.2 Recommendations

Various physical parameters of the tip vortex, such as the tangential location and strength of the tip vortex, had to be extracted from the measured acoustic data. An improved aerodynamic model of the tip vortex would reduce the amount of empiricism in the model. These improvements can be attained either through experimental measurements of flow fields or through flow-field computations.

An axisymmetric model is recommended for the tip vortex (rather than an unwrapped annulus model), due to the significant geometric and aerodynamic radial variations of the blades. Such an approach may require a numerical solution rather than the analytical (closed form) solution that has been possible with the unwrapped annulus or rectilinear array of vortices adopted in the existing model.

In the current tip vortex model, an axial velocity component of the tip vortex has not been considered, which may affect the upwash perturbation velocity as much as the tangential component of the tip vortex.

#### 5.0 References

- 1. Arndt, W.E., "Propfans Go Full-Scale," Aerospace America, pp. 100-103, January 1984.
- 2. Rauscher, M., "Introduction to Aeronautical Dynamics," John Wiley and Sons, Inc., p. 373, 1953.
- 3. Majjigi, R.K., and Gliebe, P.R., "Development of a Rotor Wake/Vortex Model," Final Report, Volume I, NASA CR-174849, June 1984.
- 4. Majjigi, R.K., and Gliebe, P.R., "Development of a Rotor Wake/Vortex Model," User's Manual for Computer Program, Volume II, NASA CR-174850, June 1984.
- 5. Tangler, J.L., Wohlfeld, R.M., and Miley, S.J., "An Experimental Investigation of Vortex Stability, Tip Shapes, Compressibility, and Noise for Hovering Model Rotors," NASA CR-2305, September 1973.
- b. Rorke, J.B., and Wells, C.D., "A Hover Performance Analysis Combining the Strip-Momentum and Prescribed Wake Theories," Proceedings Third CAL/AVLABS Symposium Aerodynamics of Rotary Wing and V/STOL (vertical/short takeoff and landing) Aircraft, Volume I, Rotor/Propeller Aerodynamics, Rotor Noise, held at Buffalo, New York, June 18 through 20, 1969.
- 7. Grow, T.L., "Effect of a Wing on its Tip Vortex," J. Aircraft, Volume 6, Number 1, pp. 37-41, January/February 1969.
- 8. Mason, W.H., and Marchman, J.F., III, "The Far-Field Structure of Aircraft Wake Turbulence," AIAA Paper Number 72-40, 1972.
- 9. Sears, W.R., "Some Aspects of Nonstationary Aerofoil Theory," Journal of Aeronautical Sciences, Volume 8, pp. 104-118, 1941.
- 10. Amiet, R.K., "Effects of Compressibility in Unsteady Lift Theories," Unsteady Aerodynamics (R.B. Kinney, ed.), Proceedings of a Symposium on Unsteady Aerodynamics, University of Arizona, pp. 631-653, March 18 through 20, 1975.
- 11. Goldstein, M.E., "Aeroacoustics," McGraw-Hill, New York City, New York, 1976.
- 12. Johnsen, I.A., et al., editors, "Aerodynamic Design of Axial Flow Compressors," NASA SP-36, 1965.
- 13. Lakshminarayana, B., "Methods of Predicting the Tip Clearance Effects in Axial Flow Turbomachinery," ASME Journal of Basic Engineering, Volume 92, Series D, pp. 467-482, September 1970.

- 14. Lamb, H., "Hydrodynamics," 6th Edition, Dover Publications, p. 224, New York, 1945.
- 15. McCormick, B.W., Tangler, J.L., and Sherrieb, H.E., "Structure of Trailing Vortices," J. Aircraft, Volume 5, Number 3, pp. 260-267, May/June, 1968.
- Donaldson, C., Snedeker, R.S., and Sullivan, R.D., "Calculation of Aircraft Wake Velocity Profiles and Comparison with Experimental Measurements," J. Aircraft, Volume 11, pp. 547-555, September 1974.
- 17. Kemp, N.H., and Sears, W.R., "The Unsteady Forces due to Viscous Wakes in Turbomachines," Journal of Aeronautic Sciences, Volume 22, Number 7, pp. 478-483, July 1955.

### 6.0 Nomenclature

a	Radius of the core of the tip vortex
AR	Aspect ratio (span/chord)
$b_{\mathbf{r}}$	Radial distance of the center of the tip vortex from rotor tip
bt	Tangential location of the center of the tip vortex in the interblade passage relative to wake centerline
B1	Number of blades in the forward rotor
B2	Number of blades in the aft rotor
c	Chord
$c_a$	Axial Chord
$C_{D}$	Local section drag coefficient
Ci	Circulation index (Equation 13.1)
CL	Local section lift coefficient
dBA	A-weighted dB level
$D_{tip}$	Tip diameter
D <sub>T1</sub>	Tip diameter of forward rotor
D <sub>T2</sub>	Tip diameter of aft rotor
$f_{s1q}$	q <sup>th</sup> harmonic of steady loading and thickness noise of forward rotor (see Equation 20)
f <sub>s2r</sub>	r <sup>th</sup> harmonic of steady loading and thickness noise of aft rotor (see Equation 21)
$f_{\mathbf{wqr}}$	r <sup>th</sup> harmonic of aft rotor unsteady noise due to q <sup>th</sup> gust harmonic
HTR	Hub/tip-ratio
$K_{\text{vtx}}$	Empirical constant for tip vortex trajectory (see Equation 19)
M <sub>∞</sub>	Aircraft Mach Number

M,N,p Parameters associated with the tip vortex (see Equations 3-5)

mwqr Spinning mode number of r<sup>th</sup> harmonic of aft rotor unsteady noise

due to qth gust harmonic of forward rotor

Exponent for decay of circulation of tip vortex (see Equation 16)

OASPL Overall sound pressure level

PNL Perceived noise level

q Gust harmonic

R Radius

r Radial distance from center of vortex core

Rhub Hub radius

R<sub>tip</sub> Tip radius

R<sub>vtx</sub> Radial location of tip vortex

R<sub>T1</sub> Tip radius of forward rotor

RPM1 RPM of forward rotor

RPM2 RPM of aft rotor

S Blade-to-blade tangential spacing

S Streamwise distance

SPL Sound pressure level

Stip Blade-to-blade tangential spacing at the tip

UDF Unducted fan

V<sub>a/c</sub> Aircraft flight velocity

V<sub>tip</sub> Tip speed

 $V_{\theta}$  Tangential velocity created by tip vortex

 $(V_{\theta})_{max}$  Maximum value of tangential velocity created by tip vortex

 $V_{\infty}$  Freestream velocity

W<sub>dc</sub> Wake centerline defect (relative to forward rotor)

W<sub>FS</sub> Freestream velocity (relative to forward rotor)

x,y Coordinates of the unwrapped annulus (see Figure 2)

X<sub>f</sub> Axial distance from pitch change axis of forward rotor

XPCA Axial distance between pitch change axes

Z<sub>vtx</sub> Axial location of tip vortex

### Greek Symbols

Γ Circulation

 $(\Gamma)_{VIX}$  Circulation of the tip vortex

δ Semiwake width

Tip clearance

ω Angular velocity of the tip vortex

# Appendix A

# User's Manual for Blade Tip Vortex Model Computer Program

The tip vortex model computer program developed for counterrotating propulsors is described in this appendix. This computer program is based on a similar program for evaluating turbofan/compressor rotor/stator interaction and also has an option to include a hub vortex (References 3 and 4). This study concentrated on developing the tip vortex model only. This appendix is divided into the following sections:

- A. Description and Flow Chart of the Computer Program
- B. Listing of the Computer Program
- C. Definition of Input/Output Parameters
- D. A Sample Input/Output Case.

### A. Description and Flow Chart of the Computer Program

The computer program predicts the wake/tip vortex flow distributions of the forward rotor and the resultant upwash gust velocity field at the aft rotor. Based on a meridional-plane stream surface subdivision of the rotor-to-rotor flowpath annulus, the program is designed to use the following as input:

- Forward rotor inlet and exit aerodynamic vector diagram parameters
- Blade section properties such as solidity, chord, and sweep
- Aerodynamic properties (such as section drag and lift coefficients), as a function of immersion.

The viscous wake and tip vortex model is programmed to predict blade-to-blade circumferential distributions of the flow field at the one-fourth-chord point of the aft rotor in a reference frame fixed to the aft rotor. The computer program has all of the logic built into it to predict the flow field due to a hub vortex, but the empirical relationships for the hub vortex characteristics have not yet been developed. The computer program is designed to transform the forward rotor-fixed wake and tip vortex combined flow velocity profiles into a reference frame fixed to the aft rotor to evaluate the gust velocity profiles. Fourier analysis of the gust velocity profiles yields the gust harmonic spectrum. An analysis for evaluating the spanwise distortion and clocking of the wake/tip vortex sheet is incorporated into the program to predict the spanwise aerodynamic phase lag of the wake/tip vortex velocity field; thereby obtaining the spanwise distribution of the amplitude and relative phase of the gust upwash harmonic content. A flow chart of this computer program is presented in Figure A-1. The computer program output (specifically, gust harmonic spectrum and aerodynamic phase lag) forms input to the computation of the unsteady lift force computation and, subsequently, noise due to wake/tip vortex interaction.




Figure A-1. Program Flow Chart for the Rotor Wake/Tip Vortex Model.




Figure A-1. Program Flow Chart for the Rotor Wake/Tip Vortex Model (Continued).




Figure A-1. Program Flow Chart for the Rotor Wake/Tip Vortex Model (Continued).




Figure A-1. Program Flow Chart for the Rotor Wake/Tip Vortex Model (Continued).




Figure A-1. Program Flow Chart for the Rotor Wake/Tip Vortex Model (Concluded).

The following specific features are incorporated into the computer program.

- Three models of predicting the centerline defect and semiwake width:
  - Linear-rational-function model (see Reference 3)
  - Kemp and Sears model
  - Mugridge and Morfey model.
- Two wake shape functions; namely:
  - Gaussian profile (e<sup>-ln2<sup>η2</sup></sup>)
  - Hyperbolic secant profile [sech  $(a_{\eta})$ ,  $a = \cosh^{-1} 2$ ].
- Tip and hub vortices are incorporated in the program with options to include both, neither, or either one of them. Certain existing empirical relationships have been used in estimating the strength and radius of the tip vortex; however at this time, no such information is available for the hub vortex model. When such correlations for estimating the strength and radius of hub vortex become available, they can be incorporated into the computer program. The computer code also gives the trajectories of the centers of hub and tip vortices.

The computer program source code contains approximately 1000 lines. It consists of:

- Main program, which manipulates input, output, and all of the subroutines. It also computes the tip-to-hub aerodynamic phase lag, once all of the streamline computations have been performed.
- Subroutine RWTVM, which combines the flow fields due to wake and tip vortex and performs the coordinate transformation from the one fixed to the forward rotor, to the one fixed to the aft rotor.
- Subroutine WAKE1, which computes the wake centerline defect and semiwake width.
- Subroutine WAKE2, which computes the tangential wake profiles.
- Subroutine VORTX1, which computes the vortex strength and radius of tip and hub vortices.
- Subroutine VORTX2, which computes the velocity field induced by tip and hub vortices.
- Subroutine HRMONIC, which computes the harmonic content of rotor wake/vortex gust.
- Subroutine GAMCAL, which computes the ratio of specific heats for air as a function of ambient temperature.

- Subroutines PITCH1 and PITCH2, which compute the blade coordinate changes (and, thus, spacing) due to changes in pitch angle, relative to design setting for forward and aft rotors, respectively.
- Subroutine LSPFIT, which is an interpolation/integration subroutine.

### **B. Listing of the Computer Program**

A listing of the computer program in the DEC/FORTRAN-77 language is included in this section.

```
DUB0: { CHARLOTTE } RWTVM. FOR; 6
```

υ

U Ú U

```
WAKE/TIP VORTEX GUST HARMONIC COMPUTATION MODEL
                                                           COMMON/COM12/ NZ, DTR, RTD, VO, CO, SXOCH(51)
                                   R.K.MAJJIGI NOV 11, 1985
```

COMMON/RWAKEL/ ISHAPE, BETAW, NWHM, VREF, IWAKE

COMMON/HMONIC/ST(300), VPN(300), FCA(21), FCB(21), FCDB(21)

COMMON/BLADE1/ THETA1(51), SIGR1(51), DPINT1(51), 1 CHORD1(51), TMOC1(51), ALPHA1(51), , FA1(51), scb1(51), Z1(51), ZMC1(51), YMC1(51), BETAP1(51), MCA1(51), FA: COMMON/PRINTD/IPRT, IPR BETPP1 (51), DELBP1 NB I EMT1 COMMON/BLADE2/ THETA2(51), SIGR2(51), DPINT2(51),
1 CHORD2(51), TMOC2(51), ALPHA2(51),
1 22(51), ZMC2(51), YMC2(51),
1 BETAP2(51), HCA2(51), FA2(51),
1 BETP2(51), DELBP2, SCD2(51), EMT 2

COMMON /VTEX2/ SAODS(2),SCIRCO(2),SOO(2),SVSDV0(2),SCL(2), COMMON /VIEX3/ SBN(2),SBR(2),SDIST,RAWDS,R,VINRVT(300,2), COMMON /VTEXI/ ITPVTX, IHBVTX, TAU, ALPHR, DUMMY, WT00, Bl COMMON /VTEX4/ CLAV, GAV, WT00T, ABR(51), CI, TVTI 1 VISRUT(300,2), HTR, VINRV(300), VISRV(300) SFRL(2)

CHARACTER\*40 CRUDF1, CRUDF2, PRINTF, LOTF CHARACTER DAT\*9, TIM\*8

DIMENSION Z(10),ZMC(10),YMC(10)

DIMENSION TMOC(10),BETAP(10),THETA(10),ALPHA(10),CHORD(10)

DIMENSION CL1(51),EMR1(51)

DIMENSION CL2(51),EMR2(51)

DIMENSION XC1(51),YC1(51),XI(51),XI(51),AAA(51),XC2(51),YC2(51) DIMENSION EMRR(51), SPARE(51) DIMENSION SCD(10) DIMENSION AEROPH(51)

REAL MCA, MCA1, MCA2

DATA IWAKE,IRW,IQHAXR/2,1,10/
IWAKE=1 LINEAR RATIONAL FUNCTION MODEL FOR ROTOR WAKE
IWAKE=2 SILVERSTEIN/KEMP & SEARS MODEL FOR ROTOR WAKE
IWAKE=3 MUGRIDGE & HORFEY MODEL FOR ROTOR WAKE
DATA WTIV,PCTCL,BETAW,IPRNTW,ISHAPE/0.,0.,0.,0,2/
DATA VREF,IHBVTX,TAU/10.0,0,10.0/ DATA RG/1716.26/

DATA PCTVTX/30./

CI=CIRCULATION INDEX FOR TIP VORTEX CALCULATIONS
CI=1.0(DEFAULT)

OPHORNAL CONTROL 

U

Ų

U

U

67

U U

000

U

00000

6-NOV-1987 14:22

DATA CI 1.0/

TVTI=TIP VORTEX TRAJECTORY INDEX, TVTI=2.0 (DEFAULT)

DATA TVTI/2.0/

```
0 0 0 0
                     U
```

ISHAPE, BETAW, NWHM, VREF, NSTEP, IPRNTW, NAMELIST/INPUT/NCASE, VO, TAMB, PAMB, NP,

XPCA, WTIV, PCTCL,

DT.NB.SHP, RPM, CHORD, TMOC, ALPHA, THETA, BETAP, DELBP, BETA34, HTR, ZMC, YMC, SCD, IRW, IWAKE,

ITPUTX, IHBUTX, SBN, PCTUTX, TAU, CI, TUTI

```
INITIALIZE CONSTANTS
0 0 0 0 0
```

```
OPEN(15, READONLY, STATUS='OLD')
                                                                                                       READ(15,9000) CRUDF1
PI=3.1415926
TPI=2.0*PI
DTR=PI/180.0
                                              RTD=1.0/DTR
                                                                                                                        I 1 = 1
```

```
IF(CRUDF1(I:I).EQ.'.'.OR.CRUDF1(I:I).EQ.' ') THEN
              Do I=1,40
IF(CRUDF1(I:I).EQ.']') I1=I+1
IF (CRUDE1(1:1).EQ. '[') THEN
                                                                                                                                           CRUDF1=CRUDF1(1:NC)//'.DAT'
                                                                                          DO I=11,40
                                                                                                                                                                GO TO 8001
                                                    END DO
                                                                                                                                                                                   END IF
                                                                                                                             NC = I - 1
```

```
IF(CRUDE2(I:I).EQ.'.'.OR.CRUDE2(I:I).EQ.' ') THEN
OPEN(UNIT=10,FILE=CRUDF1,STATUS='OLD',SHARED)
                                                                                                                    IF(CRUDF2(I:I).EQ.'|') I1=I+1
                                                                   IF(CRUDE2(1:1).EQ. '[') THEN
                      READ(15,9000) CRUDF2
                                                                                                                                                                                           DO I=11,40
                                                                                               DO I=1,40
                                                                                                                                            END DO
```

CRUDF2=CRUDF2(1:NC)//'.DAT' GO TO 8002

8001

END DO

о 68

```
CALL READNL(10,0,INPUT,'INPUT',1,' ','INPUT',1,IBW,IEW)
                                                                                                                                                                               IF(PRINTF(I:I).EQ.'.'.OR.PRINTF(I:I).EQ.' ') THEN
                                         OPEN(UNIT=11, FILE=CRUDF2,STATUS='OLD',SHARED)
READ(15,9000) PRINTF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(BETA34.NE.O.) THEN CALL LSPFIT(Z,BETAP,NZ, .75,BET34,1, 0,AAA) DELBP!=BETA34-BET34
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SET PROGRAM VARIABLES/CONSTANTS - ROTOR 1
                                                                                                                                                                                                                                                                                                                                                                                            CONTINUE
READ(10, INPUT, ERR=800, END=999)
NRSEC=0
                                                                                                                                                                                                                                                                                                                                         FORMAT(I1)
CALL SFATT(16,PRINTF,1,ISTAT)
                                                                                                                      IF(PRINTF(I:I).EQ.')') Il=I+1
                                                                                                                                                                                                                           PRINTF=PRINTF(1:NC)//'PRN'
CALL SFATT(26,LOTF,1,ISTAT)
READ(15,9002) ILOTT
GO TO 9001
                                                                                       IF (PRINTF(1:1), EQ. '(') THEN
                                                                                                                                                                                                               LOTF-PHINTF(1:NC)//'.LOT'
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               TMOC1 (ISL)=TMOC(ISL)
BETAP1 (ISL)=BETAP(ISL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  CHORDI (ISL)=CHORD(ISL)
DUBO: [CHARLOTTE]RWTVM.FOR; 6
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  ZMC1 (ISL)=ZMC(ISL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   YMC1 (IST)=XMC(IST)
                                                                                                                                                                                                                                                                                                                                                                    READ INPUT DATA FILE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     DO 90 ISL=1,NZ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     21 (IST)=Z(IST)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         YOD1=DIST/DT1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  DELBP1 = DELBP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      DXTM1=DXTM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              ITDO1 = ITDO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             ILDO1 = ILDO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              CLOSE (10)
                                                                                                                                                                      DO I=I1,40
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        XLM1=XLM
                                                                                                                                                                                                                                                                                                                                                                                                                                                  BETA34=0.
                                                                                                                                                                                                                                                                                                                            FORMAT (A)
                                                                                                            0F'1-I 00
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 HTR1-HTR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           ALE1=ALE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           BTE1=BTE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        XTM1=XTM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        NHM1 = NHM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SHP1=SHP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     RPM1=RPM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                ISECT = 0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           NB1=NB
                                                                                                                                                                                                                                                                                              END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             DT1=DT
                                                                                                                                                                                                                                                                                                             END DO
                                                                                                                                           END DO
                                                                                                                                                                                                       NC=I-1
                                                                                                                                                         END IF
                                                                                I 1 = 1
                                                                                                                                                                                                                                                                                                                            9000
9002
9001
                                                 8002
                                                                                                                                                                                                                                                                                                                                                                          с
с
100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                U
                                                                                                                                                                                                                                                                                                                                                                                                                                                    69
```

# DUB0: [CHARLOTTE]RWTVM.FOR; 6

```
OPEN(11, READONLY, STATUS='OLD')
THETAL (ISC)=THETA(ISC)
ALPHAL (ISC)=ALPHA(ISC)
                                                                            READ INPUT DATA FILE
                      SCDI (IST)=SCD(IST)
                                 CONTINUE
                                90
C-:
                                                        00000
```

READ(11, INPUT, ERR=800, END=999)

NRSEC=0

```
CALL READNL(11,0,INPUT,'1)''','INPUT',1,'BW,IEW)
PROGHAM WARIABLES/CONSTANTS - ROTOR 2
                                                                                                                   DELBP2=DELBP

IF(BETA34.NE.O.) THEN

CALL LSPFIT(Z,BETAP,NZ, .75,BET34,1, 0,AAA)

DELBP2=BETA34-BET34
                                                                                                                                                                                                                                                                                                                                                                                               CHORD2 (ISL) =CHORD(ISL)
                                                                                                                                                                                                                                                                                                                                                                                                                             BETAP2 (ISL) = BETAP (ISL)
                                                                                                                                                                                                                                                                                                                                                                                                                                             THETA2(ISL)=THETA(ISL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                           ALPHA2 (ISL)=ALPHA(ISL)
                                                                                                                                                                                                                                                                                                                                                                                                               TMOC2 (IST)=TMOC(IST)
                                                                                                                                                                                                                                                                                                                                                                  ZMC2 (ISL)=ZMC(ISL)
                                                                                                                                                                                                                                                                                                                                                                                 YMC2 (IST) =XMC(IST)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         SCD2 (IST)=SCD(IST)
                                                                                                                                                                                                                                                                                                                                  DO 91 ISL=1,N2
                                                                                                                                                                                                                                                                                                                                                   22(IST)=2(IST)
                                                                                                                                                                                                                                                                                                      YOD2=DIST/DT2
                                                                                                                                                                                                             ITD02=ITD0
                                                                                                                                                                                                                             ILD02=ILD0
                                                                                                                                                                                                                                                                                        DXTM2=DXTM
BETA34=0.
                                                                                                                                                                                                                                                                                                                   XLM2=XLM
                                                                         NHM2=NHM
                                                                                                       RPM2=RPM
                                                                                                                                                                                               HTR2=HTR
                                                                                                                                                                                                                                           ALE2=ALE
                                                                                                                                                                                                                                                           BTE2=BTE
                                                                                                                                                                                                                                                                         XTM2=XTM
                                                                                       SHP2=SHP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        CONTINUE
                                                          NB2 = NB
                                                                                                                                                                                END IF
                                             DT 2 = DT
                            SET
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       16.00
10.00
10.00
                              U
                                                                                                                                                                                                                                                       70
```

FORMAT(4X, 'BETAP SURFACE APPROXIMATION MODEL'//
1
4X, 'WAKE/VORTEX MODEL INCLUDED'//)

FORMAT(//,1H0,16x,15H\*\*\*\* RWTVH \*\*\*\*//,
1 4x,33HUDF ROTOR GUST PREDICTION PROGRAM//)

OPEN (26, STATUS='NEW') OPEN(16, STATUS='NEW')

WRITE(16,500) WRITE(16,505)

200 505 FORMAT(//16X,17H"\*\*\*\* RWTUM \*\*\*\*"/,
1 4x,35H"UDF ROTOR GUST PREDICTION PROGRAM"//)

WRITE (26,9500)

9500

ORIGINAL PAGE IS OF POOR QUALITY

## DUB0: [ CHARLOTTE ] RWTVM. FOR; 6

CALL DATE (DAT)

```
- CASE NO.', I3, 4H ***//
                                                                                                                                                                                                                                                                   CASE NO.', I3, 4H ***//)
              WHITE(16,517) CRUDF1, CRUDF2, DAT, TIM
WHITE(16,517) CRUDFILE IS ', A40//2X,'AFT CRUDFILE IS ', A40//
1 2x,'DATE; ', A9,', TIME; ', A8//)
                                                                                                  WHITE(20,9517) CRUDF1, CRUDF2, DAT, TIM
FORMAT(2X, "FORWARD CRUDFILE IS "', "', A40, "'//
1
2X, "AFT CRUDFILE IS "', "', A40, "'//
1
2X, "DATE; "', "', A9, "', "', TIME; "', "', A8, '"'//)
                                                                                                                                                                                                                                                                                                                                                                  WRITE(16,515)DT2,NB2,SHP2,RPH2,VO,TAMB,PAMB,NP
FORMAT(10X,28HPROPELLER TIP DIAMETER DT = F8.4,5H FT.//
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           DEG. F//
                                                                                                                                                                                                                                                                                                                                                                                                                                                           = F10.1//
= F8.2//
= F8.2,8H DEG. F,
= F8.3,5H PSIA//
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    PRELIMINARY AERODYNAMIC PARAMETER CALCULATIONS *****
                                                                                                                                                                                                                                                                                             WRITE(16,515) DTI, NBI, SHPI, RPMI, VO, TAMB, PAMB, NP WRITE(16,511) KASE FORMAT(7X, *** ROTOR 2 INPUT PARAMETERS - CAS
                                                                                                                                                                                                                                                                                                                                                                                                                                      = F10.2//
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             = 13,//)
                                                                                                                                                                                                                                                                                                                                                                                                                //51 =
                                                                                                                                                                                                                                                 WRITE(16,510)KASE
FORMAT(7X,'*** ROTOR 1 INPUT PARAMETERS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        WRITE(10,516)XPCA, IRW, IWAKE
FORMAT(10X, 'XPCA = ',F7.4/10X, 'IRW
1 10X, 'IWAKE=',I2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             10X, 28HAMBIENT TEMPERATURE TAMB
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         10X, 28HFLIGHT VELOCITY VO (FPS)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           10X, 28HNUMBER OF PROPELLERS NP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     10X, 28HAMBIENT PRESSURE PAMB
                                                                                                                                                                                                                                                                                                                                                                                                                                          1 10x, 28HSHAFT HORSEPOWER SHP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1 10x, 28HROTATIVE SPEED (RPM)
                                                                                                                                                                                                                                                                                                                                                                                                                    1 10x, 28HNUMBER OF BLADES NB
CALL TIME (TIM)
                                                                                                                                                                                                                                     KASE=KASE+1
                                                                                                                                            9517
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          516
                                                517
                                                                                                                                                                                                                                                                                     510
                                                                                                                                                                                                                                                                                                                                                            511
                                                                                                                                                                                                                                                                                                                                                                                                        515
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             o
71
```

ORIGINAL PAGE IS OF POOR QUALITY

```
WCON1 = 0.25*GAMMA*PO*CO*EMO*EMT1*B1*DT1*DT1
                                                                                                                                                                                  PCON1=GAMMA*PO*B1/(4.0*PI*SQRT(2.0))
                                                                                                                                                                                                                              MACH NO. =F8.4//)
                                                                                                                                 EMH1 = SQRT (EMT1 * * 2+EMO * * 2)
                                                                           CALL GAMCAL(TAMB, GAMMA)
                                                                                          CO=SQRT (GAMMA*RG*TO)
                                                                                                                                                                        ADVRI=VO/(RPS1*DT1)
                                                                                                                                                                                                                                 1 15x, 20HHELICAL
                                                                                                                                                                                                                                                                                        UT2=FI*DT2*RPS2
                        UT1 = PI * DT1 * RPS1
                                                                                                                                                                                                                                                              RPS2=RPM2/60.0
RPS1=RPM1/60.0
                                                                RHO=PO/(RG*TO)
                                                 PO=144.0*PAMB
                                    TO=TAMB+459.7
                                                                                                           EMT1=UT1/CO
                                                                                                                        EMO=VO/CO
                                                                                                                                                                                                                                                                            B2=NB2
            B1=NB1
                                                                                                                                                                                                          520
                                                                                                                                                                                                                                                   U
```

```
Page 6
```

```
___DUB0: [CHARLUTTE]RWTVM.FOR; 6
```

6-NOV-1987 14.22

```
DPINTI(IZ)=GAMMA*EMTI*Z1(IZ)*EMR1(IZ)*THETA1(IZ)/SIGR1(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       C
C
C*** ROTOR EFFECTIVE AERODYNAMIC HORSEPOWER AND DISK LOADING ***
C
                                                                                                        C
C
C*** BLADE SECTION PROPERTIES CALCULATION - ROTOR 1 ***
C
C
                              WCON2=0.25*GAMMA*PO*CO*EMO*EMT2*B2*DT2*DT2
PCON2=GAMMA*PO*B2/(4.0*PI*SQRT(2.0))
ADVR2=VO/(RPS2*DT2)
                                                                                                                                                                                                                                                                                                                                                 DPINTI(IZ)=THMODI*DPINTI(IZ)
CLI(IZ)=CLCON*DPINTI(IZ)
YCI(IZ)=EMRI(IZ)*CLI(IZ)*CHORDI(IZ)*21(IZ)
CONTINUE
                                                                                                                                                                                                                                                                                                     EMR1 (IZ)=SQRT(EMO**2+(EMT1*21(IZ))**2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      CALL LSPFIT(Z1, YC1, NZ, X1, Y1, 2, -1, AAA) IF(Z1(1), GT.Z1(NZ)) Y1(2)=-Y1(2)
                                                                                                                                                                                                                                                                                                                      CLCON=2.0/(GAMMA*EHR1(IZ)*EMR1(IZ))
                                                                                                                                                                                                                                                                                      SIGRI(IZ)=B1*CHORD1(IZ)/(PI*21(IZ))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                ZVTX=21(1)-PCTVTX*(21(1)-HTR1)/100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(21(1), LT. 21(NZ)) GO TO 21
                                                                                      WRITE(16,520) EMT2, EMO, EMH2
                  EMH2=5QRT(EMT2**2+EMO**2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    IF (21(12).LE.ZVTX) THEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            DO IZ=1,IZVTX
SCLAV=SCLAV+CL1(IZ)
SCAV=SCAV+CHORD1(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   FIZVTX=FLOAT(IZVTX)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    CLAV = SCLAV/FI2VTX
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      CAV = SCAV/FIZVTX
                                                                                                                                                                                                                                                                    DO 10 12=1,NZ
EMT 2 = UT 2/CO
                                                                                                                                                                                               CALL PITCHI
                                                                                                                                                                                                                                  THMOD1=1.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   DO 12=1,NZ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    XI(2)=HTR1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           XI(1)=HTR1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            XI(2)=1.0
YI(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 XI(1)=1.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      YI(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       GO TO 721
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            SCLAV=0.0
                                                                                                                                                                                                                                                    CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   IZVTX=IZ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            SCAV=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                               IZVTX=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          END DO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  END DO
                                                                                                                                                                                                                                                   700
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           721
                                                                                                                                                                                                                                                                                                                                                                                                              010
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       7
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               72
```

DUB0: [CHARLOTTE]RWTVM.FOR; 6

```
FORMAT(//18K, TABLE OF BLADE SECTION PROPERTIES - ROTOR 1'// 1 2x, THSECTION, 2x, 4HR/RT, 4x, 5HCHORD, 3x, 4HTM/C, 4x, 5HALPHA, 1 3x, 5HBETAP, 3x, 3HMCA, 5x, 2HFA, 6x, 2HCL, 6x, 'CD'//)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 CLCON=2.0/(GAMMA*EMR2(IZ)*EMR2(IZ))
DPINT2(IZ)=GAMMA*EMT2*22(IZ)*EMR2(IZ)*THETA2(IZ)/SIGR2(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          111 CONTINUE
C
C
C*** ROTOR EFFECTIVE AERODYNAMIC HORSEPOWER AND DISK LOADING ***
                                                                                                                                                                                                                                                                                                                                 DO 25 IZ=1,NZ,IPRT
WRITE(16,575)IZ,Z1(IZ),CHORD1(IZ),TMOC1(IZ),ALPHA1(IZ),
1 BETPP1(IZ),MCA1(IZ),FA1(IZ),CL1(IZ),SCD1(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                SIGR2(IZ)=B2*CHORD2(IZ)/(PI*22(IZ))
Emrr(IZ)=sqrt{Emo**2+(Z2(IZ)*Emt2+THETA1(IZ)*THMOD1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            BLADE SECTION PROPERTIES CALCULATION - ROTOR 2 ***
                                                                                                               PRINT-OUT BLADE SECTION PROPERTIES - ROTOR 1 ***
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  YC2(I2)=EMRR(IZ)*CL2(I2)*CHORD2(IZ)*Z2(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         EMR2(IZ)=EMRR(IZ)
EMR2(IZ)=SQRT(EMO**2+(EMT2*Z2(IZ))**2)
                IF(ABS(SHPI-SHPEI). LE. 0.01) GO TO 710
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        ZCL=Z2(1)-PCTCL*(Z2(1)-HTR2)/100.
                                                                                                                                                                                                                                                                                                                                                                                                                              FORMAT (16, 2X, 3F8.4, 2F8.2, 4F8.4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      DPINT2(IZ)=THMOD2 * DPINT2(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(22(1).LT.Z2(NZ)) GO TO 22
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                IF (PCTCL.EQ.0.) GO TO 701
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            CL2(I2)=CLCON*DPINT2(I2)
SHPE1=WCON1 *YI(2)/550.0
                                                                                                                                                                                                                                                                                                            IF(NZ.GT.15) IPRT=NZ/10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  IF(Z2(IZ).LE.ZCL) THEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  1 *21(IZ)*EMT1)**2)
                                              THMOD1 = SHP1/SHPE1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        XI(2)=22(IZCL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    N2CL=N2-I2CL+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                DO 11 12=1,NZ
                                                                                                                                                                                     WRITE(16,570)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       CALL PITCH2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              DO 12=1, NZ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               XI(1)=HTR2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     THMOD2=1.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                XI(1)=0.0
                                                                      GO TO 700
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     GO TO 701
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          CONTINUE
                                                                                                                                                                     CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               12CL=12
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 END DO
                                                                                                                                                                                                                                                                                      IPRT=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IZCL=1
                                                                                              ...
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          701
                                                                                                                                                                     710
                                                                                                                                                                                                                570
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   U
```

```
DUBO: [CHARLOTTE] RWTVM. FOR; 6
```

XI(1)=22(IZCL)

```
FORMAT (//18X, 'TABLE OF BLADE SECTION PROPERTIES - ROTOR 2'//
                                                                                                                                                                                                                                                                                                                                                                          1 2X, 7HSECTION, 2X, 4HR/RT, 4X, 5HCHORD, 3X, 4HTM/C, 4X, 5HALPHA,
                                                                                                                                                                                                                                                                                                                                                                                           1 3X,5HBETAP,3X,3HMCA,5X,2HFA,6X,2HCL,//)

DO 26 IZ=IZCL,NZ,IPRT

WRITE(16,575)IZ,22(IZ),CHORD2(IZ),TMOC2(IZ),ALPHA2(IZ),

BETPP2(IZ),MCA2(IZ),FA2(IZ),CL2(IZ)
                                                                       CALL LSPFIT(22(IZCL), YC2(IZCL), NZCL, XI, YI, 2, -1, AAA)
IF(Z2(1), GT.22(NZ)) YI(2)=-YI(2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     CALCULATE ROTOR - ROTOR GUST LOADING HARMONICS ****
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            RMC1=SQRT(YMC1(IZ)*YMC1(IZ)+ZMC1(IZ)*ZMC1(IZ))
                                                                                                                                                                                                                           C C*** PRINT-OUT BLADE SECTION PROPERTIES - ROTOR 2 ***
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      FORMAT(/15X,21HEFFECTIVE AERO SHP = F8.2/
1 15X,21HROTOR ANNULUS AREA = F8.3,6H SQ FT/
1 15X,21HDISK LOADING SHP/D2 = F8.2/
1 15X,21HDISK LOADING SHP/AA = F8.2/
1 15X,21HPOWER COEFFICIENT CP= F8.3//)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            CPQ1=550.0*SHPE1/(RHO*(RPS1**3)*(DT1**5))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         CPQ2=550.0*SHPE2/(RHO*(RPS2**3)*(DT2**5))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       FORMAT(//15%,'ROTOR 2')
WRITE(16,580) SHPE2,AA2,DL12,DL22,CPQ2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   WRITE(16,580) SHPE1, AA1, DL11, DL21, CPQ1
                                                                                                                                              IF(ABS(SHP2-SHPE2).LE.0.01) GO TO 711
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      =0.25*PI*DTI*DTI*(1.0-HTRI*HTRI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               -0.25*PI*DT2*DT2*(1.0-HTR2*HTR2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(RMCI.GT..00001) THEN
PSI1=ATAN2(ZMCI(IZ),YMCI(IZ))
YMCIP=RMCI*COS(PSII+DELBPI*OTR)
ZMCIP=RMCI*SIN(PSII+DELBPI*OTR)
                                                                                                                           SHPE 2=WCON2 * YI (2) /550.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            FORMAT(//15x, 'ROTOR 1')
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       IF (IRW. LE. 0)GO TO 660
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              DL11=SHPE1/(DT1*DT1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         DL12=SHPE2/(DT2.DT2)
                                                                                                                                                                         THMOD2=SHP2/SHPE2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                DL22=SHPE2/AA2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            DO 650 IZ=1,NZ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     DL21=SHPE1/AA1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 WRITE(16,578)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                WRITE (16,579)
                                                                                                                                                                                                                                                                                                                        WRITE(16,571)
XI(2)=HTR2
                           VI(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           26 CONTINUE C C ** ROTOR 1 **
                                                    CONTINUE
                                                                                                                                                                                                                                                                                                   CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        I 2 R = I Z
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        ROTOR 2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            * U
                                                                                                                                                                                                                                                                                                                                                 571
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          578
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            580
                                                                                                                                                                                                                                                                   υ
                                                    22
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              74
```

ZMC1P=0.

XMC1P=0

```
RMC1=SQRT(YMC1(IZ)*YMC1(IZ)+ZMC1(IZ)*ZMC1(IZ))
IF(RMC1:GT..00001) THEN
PSI1=ATAN2(ZMC1(IZ),YMC1(IZ))
YMC1P=RMC1*COS(PSI1+DELBP1*DTR)
ZMC1P=RMC1*SIN(PSI1+DELBP1*DTR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          THTEL=THMC1+CHORD1(IZ)*COSBP1/Z1(IZ)
RMC2=SQRT(YMC2(IZ)*YMC2(IZ)+ZMC2(IZ)*ZMC2(IZ))
          RMC2=SQRT(YMC2(IZ)*YMC2(IZ)+ZMC2(IZ)*ZMC2(IZ))
IF(RMC2-GT..00001) THEN
                                                                                                                                                                                            SXOCH(IZ)=([ABS(XPCA)-ZMCIP-CHORDI(IZ)*

SIN(BETPP1(IZ)*DTN)/2.)+

DT2/DT1*(ZMC2P-CHORD2(IZ)*

SIN(BETPP2(IZ)*DTN)/2.)]/CHORDI(IZ)

CALL RWVH(IZR,NSTEP,IPRNTW,WTIV,THMODI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    Z I
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         WU1 = Z1 (IZ) *UT1 * (1.-THETA1 (IZ) *THMOD1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  *** INDEX OVER SPANWISE LOCATION INDEX
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   PSIZ=ATAN2(ZMC2(IZ),YMC2(IZ))
YMC2P=RMC2*COS(PSIZ+DELBP2*DTR)
ZMC2P=RMC2*SIN(PSIZ+DELBP2*DTR)
                                                  PSI2=ATAN2(ZMC2(IZ), YMC2(IZ))
YMC2P=RMC2*COS(PSI2+DELBP2*DTR)
ZMC2P=RMC2*SIN(PSI2+DELBP2*DTR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          SINBPL=SIN(DTR*BETPP1(IZ))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              COSBP2=COS(DTR*BETPP2(IZ))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SINBP2=SIN(DTR*BETPP2(IZ))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         COSBP1=COS(DTR*BETPP1(12))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     IF (RMC2.GT..00001) THEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     THMC1=2.0*YMC1P/Z1(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   BR1 = ATAN2 (WU1, VO)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             DO 3000 IZ=1,NZ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   TB1=WU1/VO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   YMC1P=0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        ZMC1P=0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           YMC2P=0.
                                                                                                                                                                                                                                                                                                                            CONTINUE
                                                                                                                                                                                                                                                                                                                                               CONTINUE
                                                                                                                                        YMC 2 P = 0.
                                                                                                                                                           ZMC2P=0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       122=12
                                                                                                                                                                                END IF
END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                ELSE
                                                                                                                     ELSE
                                                                                                                                                                                                                                                                                                                            650
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          υ
75
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           Ų
```

ZMC2P=0.

ORIGINAL PAGE IS POOR QUALITY

```
6-NOV-1987 14.22
```

```
SUBROUTINE RWVM(IZR,N,IPRNTW,WTIV,THMODI)
COMMON/RWAKEL/ ISHAPE,BETAW,NWHM,VREF,IWAKE
DIMENSION THETAW(300),BETA(300),WT(300),WS(300),WN(300),VT(300),
I VN(300),VS(300),ALPHA(300),VTP(300),VPS(300),
I WTO(300),WTTF(300),WSC(300),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  COMMON /HMONIC/ ST(300), VPN 300), FCA(21), FCB(21), FCDB(21)
COMMON /FANVTX/ NSTR, SSIGR(51), SSEMA(51), SSTHET(51), SSEMT(51)
COMMON/BLADE1/ THETA1(51), SIGR1(51), DPINT1(51),
1 CHORD1(51), THOC1(51), ALPHA1(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                FORMAT(8X, 'STREAMLINE NO.', 5X, 'AERO PHASE LAG, DEG.')
                                                                                                                                                                                                  COMMON/BLADE2/ THETA2(51), SIGR2(51) , DPINT2(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                    FORMAT(//15X,'HUB-TO-TIP AERODYNAMIC PHASE LAG')
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   COMMON/COM12/ NZ, DTR, RTD, VO, CO, SXOCH(51)
                                                                                     THQC2=THMC2-.5*CHORD2(IZ)*COSBP2/Z2(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 , FA1(51),
, SCD1(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           FA2(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                SCD2(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           CHORD2(51), TMOC2(51) , ALPHA2(51),
                                                                THLE 2=THMC2-CHORD2(IZ) *COSBP2/22(IZ)
                                                                                                                                                                                                                                                 DTHW1=2. *XQCHQC*TB1*CH1AX/21(I2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    22(51), ZMC2(51), YMC2(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              21(51), ZMC1(51), YMC1(51),
YMC2P=HMC2*COS(PSI2+DELBP2*DTR)
                      ZMC2P-RMC2*SIN(PSI2+DELBP2*DTR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               1 WNC(300), PHI(10), WTOT(300)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 BETAP1(51), MCA1(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             MCA2(51) ,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                WRITE(16,690)IZ, AEROPH(IZ)
                                                                                                                                                                                                                                                                                                                    IF(IZ.EQ.1) DPHTIP=DELPHW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              COMMON/PRINTD/ IPRT, IPR
                                                                                                                                                                                CHIAX=CHORDI(IZ) *SINBPI
                                                                                                                                                                                                                                                                                                                                                                AEROPH ( 122 ) = DELPHW*RTD
                                                 THMC2=2.0*YMC2P/Z2(IZ)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      BETPP1(51), DELBP1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  BETPP2(51), DELBP2
                                                                                                                                                                                                                                                                                                                                         DELPHW=DELPHW-DPHTIP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           FORMAT(10X, I3, F19.6)
                                                                                                                                                                                                                                                                                               DELPHW=THW1-THQC2
                                                                                                                                                                                                                                                                          THW1 = THTE1 + DTHW1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               BETAP2(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             DO 3010 IZ=1,NZ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   WRITE(16,680)
                                                                                                                                                                                                                                                                                                                                                                                                                                                       WRITE(16,670)
                                                                                                                  THMC 2 = - THMC 2
                                                                                                                                        THLE 2 = .. THLE 2
                                                                                                                                                               THUC 2 = - THUC2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                             CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  EMTI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    STOP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        0696
76
                                                                                                                                                                                                                                                                                                                                                                                          с
3000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                              670
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          680
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                υv
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         υ
```

U

```
VTEX2/ SAODS(2), SCIRCO(2), SOO(2), SVSDV0(2), SCL(2),
                                                                       COMMON .VTEX3/ SBN(2),SBR(2),SDIST,RAWDS,R,VINRVT(300,2),
1 VISHVT(300,2),HTR,VINRV(300),VISHV(300)

COMMON .VTEX4/ CLAV,CAV,WT00T,ABR(51),CI,TVTI

CI=CIRCULATION INDEX FOR TIP VORTEX

TVTI=TIP VORTEX TRAJECTORY INDEX
                          COMMON /VIEXI/ ITPVIX, IHBVIX, TAU, ALPHR, CHORD, WT00, B1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(ITPVTX.EQ.0.AND.IHBVTX.EQ.0) GO TO 300
IF(IZR.NE.1) GO TO 310
SIGIT=SIG1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            BETA0=ATAN2((1.-STHETA)*SEMT,SEMA)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          SIMILARITY AND CORRELATION CALCULATIONS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       ALPHS=ATAN2(STHETA*SEMT,SEMA)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(IPR. EQ. 1) WRITE(16, 1210) CD
                                                                                                                                                                                                                                                                                                                                                                 - 12R
                                                                                                                                                                                                                                                                    IF (12R.EQ.1+IP*IPRT) THEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 STHETA=THETA1(IZR) *THMOD1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      SADINS=90.0-BETPP2(IZR)
                                                                                                                                                                                                                                                                                                                                       C C INDEX OVER STREAMLINE NUMBER
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       SADIN=90.0-BETPP1(12R)
DUB0: (CHARLOTTE)RWTVM.FOR; 6
                                                                                                                                                                                                                                                                                                                                                                                               WRITE (16,1200) IZR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      SEMT=EMT1 * 21 ( IZR )
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    SXOCH1=SXOCH(I2R)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       SIGS1 = SIGR2 (IZR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     SIG1 = SIGR1 ( 12R)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      VWHEEL-SEMT*CO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           VVTR=EMT2/EMT1
                                                                                                                                                                                                                                                                                                    WRITE(16,1100)
WRITE(16,1110)
                                                                                                                                                                             REAL MCAL, MCA2
PI=4. ATAN(1.)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   CD=SCD1 ( 12R)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            ALPHR-BETA0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          SEMA=VO/CO
                                                                                                                                                                                                                                                       DO IP=0,11
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             C WAKE PARAMETERS
C
                                                                    SFRL(2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         R=Z1 ( IZR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       ISTR-IZR
                                                                                                                                                                                                                                                                                                                                                                                                                 GO TO 10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             FOPT=1.0
                                                    COMMON
                                                                                                                                                                                                                                                                                                                                                                                                                                END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                END DO
                                                                                                                                                                                                            B1=NB1
                                                                                                                                                                                                                          B2=NB2
                                                                                                                                                                                                                                         IPR=0
                                                                                                                                                                                                                                                                                           I PR = 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                .
10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    Ü
                                                                                                                                    000
```

77

DUB0: [CHARLOTTE]RWTVM.FOR;6

```
CALL WAKE! (IMAKE, CD, SDIST, WT00, ALPHR, BETAO, SIG1, WTDC, DL0)
If (IPR.EQ.1) THEN
WRITE (16,1330) WT00
WRITE (16,1345) SXOCH(IZR)
WRITE (16,1345) SDIST
WRITE (16,1350) SDIST
WRITE (16,1350) DL0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                    C DETERMINE RELATIVE, ABSOLUTE, AND PERTURBATION VELOCITIES
                                                                                                                                                                                                                                                                                                                                                                                                                                       C SPECIFY ANALYSIS TRAVERSE DISTANCE STEP SIZE
                                                   CALL VORTXI(SIGIT, SEMAT, STHETAT, SEMTT)
GO TO 310
IF(IZR. EQ.1) WRITE(06,1120)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           DO 510 I=2,N
THETAW(I)=THETAW(I-1)+SI
ST(I)=THETAW(I)/(2.*ABS(THETAW(I)))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     THETAW!1)=-ENPS*SI
ST(1)=THETAW(1)/(2.*ABS(THETAW(1)))
                                                                                                                                                                   SXOCH1=SXOCH1+0.25*B1/B2*SIGS1/SIG1
WT00=SEMA/(SEMT*COS(BETA0))
                                                                                                                              C W(N) EVALUATED AT STATOR 1/4 CHORD POINT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       C DETERMINE INVISCID DISTRIBUTION OF WT C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 WTIF(I)=WTIF(I-1)-WTINC
                                                                                                                                                                                                                                             SDIST = SXOCH1/COS (BETA0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              BETA0 = BETA0 * DTR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     RNPS-FLOAT (NPS)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              WTINC=WTIV/RNI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             DO 520 I=2,ND2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    DO 530 I=N22,N
                STHETAT - STHETA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                RNI=FLOAT(NI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         NPS=(N-1)/2
S=2.*PI/BNB
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                WT0(1)=WT00
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        ND2=(N+1)/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      WTIF(1) = 1.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       RN=FLOAT(N)
                                   SEMTT-SEMT
SEMAT-SEMA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            N22=ND2+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   SI=S/RNI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     CONTINUE
                                                                                                                                                                                                           BNB=NB1
                                                                                                                                                                                                                                                                                                                                                                                                  END IF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              NI = N - 1
                                                                                             300
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       210
                                                                                                                                                                    310
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    520
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     78
```

DUB0: (CHARLOTTE)RWTVM. FOR; 6

```
SPECIFY EXIT-FLOW TOTAL RELATIVE VELOCITY PROFILE
WIIF(I)=WIIF(I)+WIIV/2.+(N22-I) *WTINC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       WTOT(I)=WTOT(I)*WTIF(I);WT0(I)-WTDC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              WTOT(I)=WTDC*(1,-PPT)
WTOT(I)=WTOT(1)*WTIF(1)+WT0(1)-WTDC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     CALL WAKE2 (IWAKE, ISHAPE, DT1, PP1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                              CALL WAKE2 (IWAKE, ISHAPE, DT1, PP1)
                                                    C DETERMINE TANGENTIAL ANGLE DISTRIBUTION
C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  C CALCULATE RELATIVE VELOCITY COMPONENTS
C BETDEL=BETA(I)-BETA(I)
C WS(I)=WT(I)*COS(BETDEL)
C WN(I)=WT(I)*SIN(BETDEL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    WT(I)=WT(I) *WTIF(I)+WTO(I)-WTDC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               DT1=(THETAW(I)-S)/DL
CALL WAKE2 (IWAKE,ISHAPE,DT,PP)
WT(I)=WTDC*(1.-PP)
                                                                                                                                                                                                                                                                                                                                                                                      CALL WAKE2 (IWAKE, ISHAPE, DT, PP)
WT(I)=WTDC*(I.-PP)
                                                                                                                                                                                                                                                                                                                                                                                                                           WT(I)=WT(I)*WTIF(I)+WT0(1)-WTDC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    BETA(I)=BETA(I)+BETAW*EXP(PP)
                                                                                                                                                                                                                                                                                                                                                                                                                                                             BETA(I)=BETA(I)+BETAW*EXP(PP)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               DEL=WTOT (INIDDL)-WT (IMIDDL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  BETDEL=BETA(I)-BETA(I)
WS(I)=WTOT(I)*COS(BETDEL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         WTOT(I)=WTDC*(1.-PPT)
                                                                                                                                                                                                                                                                                                                                                          DT1=(THETAW(I)+S)/DL
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  WTOT(I)=WTOT(I)-DEL
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            DO 500 I=IMIDLI,N
                                                                                                                                                                                                 IMIDDL=(N+1)/2
DO 550 I=1,IMIDDL
                                                                                                                                                                                                                                                                                                                                       DT=THETAW(I)/DL
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IMIDE1 = IMIDDE+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              DT-THETAW(I)/DL
                                                                                      BETAW-BETAW DTR
                                                                                                                                              BETA(I)=BETA(I)
                                                                                                                                                                                                                                                                                                   DLSOP=DLSPP/2.
                                                                                                        BETA(1)=BETA0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   N' 1=1 072 OG
                                                                                                                             DO 540 I=2,N
                                                                                                                                                                                                                                                                                      DLSPP=DL0 *S
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         PPT=PP+PP1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   PPT=PP+PP1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                CONTINUE
                   CONTINUE
                                                                                                                                                                                                                                                                                                                          DL=DLSOP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     CONTINUE
                                                                                                                                                              CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                I = II
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                560
C
                                                                                                                                                                 5 4 0
C
                      530
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        0 0 0 0
                                                                                                                                                                                                                                     υυυ
                                                                                                                                                                                                                                                                                                                                                                             U
```

79

```
Page 14
```

```
DUBO: (CHARLOTTE)RWTVM.FOR; 6
```

WN(I)=WTOT(I) \*SIN(BETDEL)

6-NOV-1987 14:22

```
RAWDS=B1/(2.*PI)
CALL VORTX2(ISTR,NST,SIG1T,SEMAT,STHETAT,SEMTT,SEMT,SIG1)
INTEGRATE WAKE AND VORTEX GUST DESCRIPTIONS
                                                                                                                                                                                                                                                                                                                                                                                  IF (ITPUTX:EQ.O.AND.IHBUTX.EQ.O) VISRV(I)=0.

IF (ITPUTX.EQ.O.AND.IHBUTX.EQ.O) VINRV(I)=0.

WSC(I)=VISRV(I)+WS(I-NO)

WNC(I)=VINRV(I)+WN(I-NO)
                                                                                                                                                                                                                                                  IF (ITPUTX.EQ.O.AND.IHBUTX.EQ.O) VISRV(I)=0.
IF (ITPUTX.EQ.O.AND.IHBUTX.EQ.O) VINRV(I)=0.
                                                IF (ITPUTX.EQ.O.AND.IHBUTX.EQ.0) GO TO 600
                                                                                CALCULATE VORTEX INDUCED VELOCITY FIELD
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      WT(I) = (WSC(I) **2+WNC(I) **2) **0.5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             WTHN1 = WT(N1) *SIN(BETA(N1))
                                                                                                                                                                                                                                                                                    WSC(I)=VISRV(I)+WS(NO+I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              WXN1 = WT (NI) *COS (BETA(NI))
                                                                                                                                                                                                                                                                                                      WNC(I)=VINRV(I)+WN(NO+I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   ST(I)=(RLI-1.)/(RLN3-1.)
ST(I)=ST(I)*2.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        IF (AAA.GE.1.0) AAA=1.0
BETA(1)=ACOS(AAA)+BETA0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            THETAW(I)=THETAW(I-N2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       WSC(I)=MSC(I-N2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        WNC(I)=WNC(I-N2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        A'AA=WS(I)/WT(I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          RLN3=FLOAT(N3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      DO 640 I=1,N3
WS(I)=WSC(I)
WN(I)=WNC(I)
                                                                                                                                                                                                                                                                                                                                                                     DO 620 I=N1,N
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       DO 630 I=N,N3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         DO 650 I=N,N3
                                                                                                                                                                                                                                     DO 610 I=1,N1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            RLI=FLOAT(I)
                                                                                                                                                                                                   N0 = (N-1)/2

N1 = (N+1)/2
               CONTINUE
                                                                                                                                                                                                                                                                                                                    CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        N3=2*N-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             CONTINUE
                                                                                                                                                                                                                                                                                                                                                     N2=2"N0
                                                                                                                  NETEN
I = I I
                                                                                                                                                                                                                                                                                                                    610
C
                                                                                                                                                                   C
C
600
                                                                                                                                                                                                                                                                                                                                                                                                                                                       08 0
80
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     630
C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          640
C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          650
C
                                                               000
```

VTN1 = (VXN1 \*\*2+VTHN1 \*\*2) \*\*0.5

VTHN1=1.+VVTR-WTHN1

UXNI=WXNI

```
WRITE (16,1510)
DO 720 I=1,N3,10
WRITE (16,1430) I,THETAW(I),ST(I),VT(I),VS(I),VN(I),ALPHA(I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 DO 710 I=1,N3,10
WRITE (16,1430) I,THETAW(I),ST(I),WT(I),WS(I),WN(I),BETA(I)
                                                                                                                                                                                                                                                                                                                                                                                                                                      DETERMINE TOTAL PERTURBATION VELOCITY
                                                                                                                                                                                                                                                                                                                                                               VPN(I)=VN(I)
VPS(I)=VS(I)-VS(NI)
VTP(I)=(VPS(I)**2+VPN(I)**2)**0.5
                                                                                                                                                                                                                                               DETERMINE ABSOLUTE VELOCITY COMPONETS
                                                                                                          C DETERMINE ABSOLUTE VELOCITY PROFILE C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                  C PRINT NUMERICAL VELOCITY PROFILES
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF (IPRNTW. LE.0) GO TO 800
                             ALPHA(NI)=ACOS(VXNI/VTNI)
ALPONI=ALPHA(NI)-ALPHA(NI)
VS(NI)=VTNI*COS(ALPDNI)
                                                                                                                                                                                          VTH=1.0+VVTR-WTH
VT(I)=(VX**2+VTH**2)**0.5
ALPHA(I)=ACOS(VX/VT(I))
                                                                                                                                                                                                                                                                             ALPDEL=ALPHA(I)-ALPHA(N1)
VS(I)=VT(I)*COS(ALPDEL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          THETAW(I)=THETAW(I)*RTD
                                                                                                                                                                                                                                                                                                         VN(I)=VT(I)*SIN(ALPDEL)
                                                                                                                                                 WTH=WT(I)*SIN(BETA(I))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         BETA(I)=BETA(I)*RTD
ALPHA(I)=ALPHA(I)*RTD
                                                                                                                                                             WX=WT(I) *COS(BETA(I))
DUBO: [ CHARLOTTE | RWTVM. FOR; 6
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     WRITE (16,1600)
WRITE (16,1610)
DO 730 I=1,N3,10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             IF (IPR.EQ.1) THEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           WRITE (16,1410)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   WRITE (16,1500)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          WRITE (16,1420)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               DO 700 I=1,N3
                                                                                          DO 000 I=1,N3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                              CONTINUE
                                                                                                                                                                                  XM=XV
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              720
C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        710
C
                                                                                                                                                                                                                                                                                                                                                                                                                  0 9 0
9 0
8 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         700
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      υ
                                                                                                                                                                                                                                           υυυ
                                                                                                                                                                                                                                                                                                                                υυυ
```

WRITE (16,1620) I, THETAW(I), ST(I), VTP(I), VPS(I), VPN(I)

```
FORMAT (/5x,'PERTURBATION VELOCITY PROFILE RELATIVE TO AFT ROTOR')
FORMAT (/9x,'1',5x,'THETAW',5x,'S',7x,'VPT',6x,'VPS',6x,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       SUBROUTINE WAKEL (IMAKE, CD, SDIST, WT00, ALPHR, BETA0, SIG1, WTDC, DL0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            C SUBROUTINE TO CALCULATE WAKE CENTERLINE DEFECT AND SEMI-WAKE WIDTH
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          (//1x, HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW')
(/5x, 'STREAMLINE NUMBER', 13)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          FORMAT (/5x,'VELOCITY PROFILE RELATIVE TO AFT ROTOR')
FORMAT (/9x,'I',5x,'THETAW',5x,'S',8x,'VI',7x,'VS',7x,'VN',
                                                                                                                                                                                                                                                                                                                                                                                                                              FORMAT (/5x, 'CD = ', F8.4)
FORMAT (/2x, 'LINEAR RATIONAL FUNCTION ROTOR WAKE PROFILE')
FORMAT (5x, 'WFS/UT', 5x, '=', F8.4)
FORMAT (5x, 'WD/UT', 6x, '=', F8.4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 FORMAT (5X, WAKE WIDTH, 1X, '=', F8.4)
FORMAT (//2X, 'ROTOR WAKE GUST DESCRIPTION FOR CASE', I4)
FORMAT (/5X, 'VELOCITY PROFILE RELATIVE TO FORWARD ROTOR')
                                                                                                                                                                                 FORMAT (/9X,'I',5X,'THETAW',5X,'S',8X,'WT',7X,'WS',7X,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             (/5X,'STREAMLINE NO.', 2X,'AERO PHASE LAG')
                                                                                                                                                                                                                                                                                                                                                                                                            FORMAT (////2X,'--- STREAMLINE NUMBER', 13,' ---')
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1 '20*LOG(MODULUS), DB')
FORMAT (7x,13,F10.6,F11.6,F14.2)
FORMAT (//2x,'TIP-TO-HUB AERODYNAMIC PHASE LAG')
                                                                                                                                                                                                                                                                                                                                          FORMAT (///18X,'ROTOR WAKE/VORTEX FLOW PROGRAM')
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           (/8x,''NH',3x,'MODULUS',4x,'PHASE',4x
                                                                                                                                   C CALCULATE HARMONIC CONTENT OF ROTOR EXIT FLOW
                                                                                                                                                                                                                                                                                                                                                                 FORMAT (/2x,'CASE NUMBER',14)
FORMAT (/2x,'TIP VORTEX NOT INCLUDED')
                                                                                                                                                                                                                                                    CALL HRMNIC (ISTR, N, NWHM, VREF, VWHEEL)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               FORMAT (5x, 'SDIST', 6x,'=', F8.4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               1 'WN', 7X, 'BETA')
FORMAT (7X, I4, F9.2, 4F9.5, F11.5)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            FORMAT(5X,'X/C',8X,'=',F8.4)
                                                                                                                                                                                                                            IF (FOPT.NE.1.0) GO TO 810
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 FORMAT (7X, I4, F9.2, 4F9.5)
FORMAT (7X, I4, F9.2, 3F9.5)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                FORMAT (8X, I4, F12.2, F9.2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          (10X, I3, F19.6)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 -- WAKE1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         E 6X, 'ALPHA')
                                                                                                                                                                                                                                                                                                 C FORMAT STATEMENTS
CONTINUE
                                                                                                                                                                                                                                                                           CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             .NBA.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                FORMAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     FORMAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           FORMAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       FORMAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            FORMAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             RETURN
                                                                                                                                                                                     Commence
                                                                                                                                                                                                                                                                                                                                                                                                            1200
1210
1300
1330
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              1400
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1430
1500
1510
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                2240
C
                                                                                                                                                                                                                                                                                                                                              1100
                                                                                                                                                                                                                                                                                                                                                                   1110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1340
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              1345
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   1350
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         1360
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1410
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           1420
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                1600
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1610
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1720
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              2000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     2010
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           2020
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             2100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     2110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          2120
                                                                                                                                                                                                                              800
                                                                                                                                                                                                                                                                           810
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               066
730
```

```
WTDC=SQRT(CD)*A1A/SQRT(2.)*((SDIST+2.*CD)**(-.5))
DL0=CD*SIG1*(.5+EXP(-.16/CD*SDIST))*(WTDC)**(-1.0)
                                                                                                                                                                                                                                                                                                                                         WTDC=CDEXP2*((0.3675*SDIST+1.95)/(7.65*SDIST+1.0))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                LINEAR RATIONAL FUNCTION FOR ROTOR WAKE PROFILE
                                                                                                                                                                                                                                                                                                                                                                                           SILVERSTEIN/ KEMP & SEARS MODEL FOR ROTOR WAKE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          C SUBROUTINE TO CALCULATE TANGENTIAL WAKE PROFILE
                                                                                           C LINEAR RATIONAL FUNCTION FOR ROTOR WAKE PROFILE C
                                                                                                                                                                                                                                                                                                                                                                                                                                             WTDC=SQRT(CD)*(1.21*(SDIST+.3)**(-1.))
DL0=SQRT(CD)*SIG1*(0.68*(SDIST+.15)**.5)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                MUGRIDGE & MORFEY MODEL FOR ROTOR WAKE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             SUBROUTINE WAKE? (IWAKE, ISHAPE, DT, PP)
                                                                                                                                                                                          IF(SIGL.GE.1.0) GO TO 101
DLOC=((0.2375*SDIST*CDEXP1+0.034125)/
1(0.357*SDIST*CDEXP1+1.0))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   IF (IWAKE.GT.1) DL0=DL0/COS(ALPHR)
                                                                                                                                                                                                                                                                                           DL0=((0.31875*SDIST*CDEXP1+0.048)/
1 (0.208125*SDIST*CDEXP1+1.0))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                GO TO (100,200,300), IWAKE
                                                                         GO TO (100, 200, 300), IWAKE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         GO TO (110,120), ISHAPE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      IF (DL0.GE.0.5) DL0=0.5
BETA0=BETA0*180./PI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              ---- WAKE 2
DUB0: [CHARLOTTE | RWTVM. FOR; 6
                                                                                                                                                            CDEXP1=CD**(0.125)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              C END OF SUBROUTINE WAKEL
                                                                                                                                                                         CDEXP2=CD**(0.25)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    PI=4.0 *ATAN(1.)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           WIDC=WIDC *WIOO
                                                          PI=4.0'ATAN(1.)
                                                                                                                                                                                                                                               DL0=DL0C*SIG1
                                                                                                                                                                                                                                                                GO TO 102
                                                                                                                                                                                                                                                                                                                                                                  GO TO 100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      GO TO 400
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           CONTINUE
                                                                                                                                                                                                                                                                                                                                  CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                     CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                  CONTINUE
                                                                                                                                             CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         A1A=2.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            ∩
400
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         300
                                                                                                                                                100
                                                                                                                                                                                                                                                                                                                                    102
                                                                                                                                                                                                                                                                                                                                                                                                                                     200
                                                                                                                                                                                                                                                                                   101
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      Ü
                                                                                                                                                                                                                                                                                                                                                                                       υυυ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          υυ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         Ú
                                           U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          83
```

ORIGINAL PAGE 13 OF POOR QUALITY

PP=2. (EXP(1.3169579\*DT)+EXP(-1.3169579\*DT))

DUB0: [CHARLOTTE]RWTVM. FOR; 6

110

```
COMMON /HMONIC/ ST(300), VPN(300), FCA(21), FCB(21), FCDB(21)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     C SUBROUTINE HRMNIC COMPUTES HARMONIC CONTENT OF ROTOR C WAKE/VORTEX FLOW AT 1/4 CHORD POINT OF SATTOR
                                                                                                                                                                                                                                                                 GO TO (310,320), ISHAPE
PP=2. /(EXP(1.3169579*DT)+EXP(-1.3169579*DT))
                                                                                                                 GO TO (210,220),ISHAPE
PP=2..(EXP(1.3169579*DT)+EXP(-1.3169579*DT))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      SUBROUTINE HRMNIC (ISTR, N, NWHM, VREF, VWHEEL)
                                                               SILVERSTEIN/KEMP & SEARS WAKE PROFILE
                                                                                                                                                                                                                   MUGRIDGE & MORFEY WAKE PROFILE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         ----- HRMNIC ---
                                                                                                                                                                                                                                                                                                                                                                       IF (PP.LT.1.E-20) PP=1.E-20
            PP=EXP(-0.6931472*DT*DT)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         COMMON/PRINTD/ IPRT, IPR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       COMPLEX CSUM, CPWR, CERC
                                                                                                                                                                   PP=EXP(-PI*DT*DT/4.)
                                                                                                                                                                                                                                                                                                                    PP=EXP(-PI*DT*DT/4.)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               CSUM=CMPLX(0.0,0.0)
                                                                                                                                                                                                                                                                                                                                                                                                     C END OF SUBROUTINE WAKE?
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF(IPR.EQ.1) THEN WRITE (16,1000) WRITE (16,1020)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              DO 220 NH=1,NWHM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           ST(I) = ST(I) -0.5
CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        PI=4. *ATAN(1.)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          DO 100 I=NS,NF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                RNH=FLOAT (NH)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          RN=FLOAT(N)
                                                                                                                                                    GO TO 400
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          NS = (N+1)/2
GO TO 400
                               GO TO 400
                                                                                                                                                                                   GO TO 400
                                                                                                                                                                                                                                                                                                     GO TO 400
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          NF=NS+N-1
                                                                                                 CONTINUE
                                                                                                                                                                                                                                                     CONTINUE
                                                                                                                                                                                                                                                                                                                                                    CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                     RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              END IF
               120
                                                                                                200
                                                                                                                                  210
                                                                                                                                                                   220
                                                                                                                                                                                                                                                  300
                                                                                                                                                                                                                                                                                     310
                                                                                                                                                                                                                                                                                                                    320
                                                                                                                                                                                                                                                                                                                                                   100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            100
                                                                                                                                                                                                                                                                                                                                                                                                                                                       U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               U
```

```
FORMAT (///2X,'HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW')
FORMAT (/8X,'NH',3X,'2*CMOD',4X,'PHASE',4X,
1 '20*LOG(2*CMOD), DB')
FORMAT (7X,13,F10.6,F11.6,F14.2)
                                                                                                                                                                                                                                                                                                                                                                                     C SUBROUTINE VORTICES

C TIP AND HUB VORTICES

C
                                                                                                                                                                                                                                                                                                                                                                                                                                            SUBROUTINE VORTX1 (SIGIT, SEMAT, STRETAT, SEMIT)
                                                                                                                                                                                                                                                                                                                                                        --- VORTX1 ---
C RESCALE INTEGRATION INTERVAL
                                                                                                                                                                                                                                                     C END OF SUBROUTINE HRMNIC
                                                 DO 300 I=NS,NF
ST(I)=ST(I)+0.5
                                                                                                                  C FORMAT STATEMENTS
                                                                                CONTINUE
                                                                                                                                                                                                                                     RETURN
                                                                                                                                                                                                  1030
                                                                                                                                                   1000
                                                                                                                                                                    1020
                                                                                  300
                                                                                                                                                                                                                                                                                                                                                                           J
```

TO SUM OVER +VE & -VE NH FCDB(NH) = FCDB(NH) + 20.0 \* ALOG10 (VWHEEL/VREF) FCD8(NH)=20.0\*ALOG10(ABS(FCA(NH))) C NUMERICAL INTERGRATION - SIMPSON'S RULE C IF (I.EQ.NS.OR.I.EQ.NF) GO TO 200 CSUM=CSUM+VPN(I)\*CERC\*(3+ICH) CPOE=KNH\*PI\*ST(I)/0.5 CPWR=CMPLX(0.0,CPOE) CERC=CEXP(CPWR) CSUM=CSUM+VPN(I) \*CERC PHASE=ATAN (BIPC/ARPC) BIPC=AIMAG(CSUM) FCA(NH)=2. \* CMOD CMOD=CABS(CSUM) ARPC=REAL(CSUM) DO 210 I=NS,NF FCB (NH)=PHASE CSUM-CSUM-HD3 GO TO 210 CONTINUE 200 210 C υ

IF(IPR.EQ.1) WRITE (16,1030) NH, FCA(NH), FCB(NH), FCDB(NH) CONTINUE

220 ບ 85

6-NOV-1987 14:22

HD3 = (ST(NF) - ST(NS))/(3.\*(RN-1.))

I CH=1

\_DUB0: (CHARLOTTE)RWTVM.FOR; 6

6-NOV-1987 14:22

U U

### ORIGINAL PAGE IS POOR QUALITY

```
COMMON FANVIX NSTR, SSIGR(51), SSEMA(51), SSTHET(51), SSEMT(51) COMMON VIEXL/ ITPVIX, IHBVIX, TAU, ALPHR, CHORD, WT00, B1 COMMON VIEX2/ SAODS(2), SCIRCO(2), SOO(2), SVSDVO(2), SCL(2),
                                                                                        COMMON VYTEX4/ CLAV, CAV, WTOOT, ABR(51), CI, TVTI COMMON PRINTD/IPRT, IPR
                                                                                                                                                                                                                                                                                                                                     BETAU=ATAN((1.-STHETA)*SEMT/SEMA)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                   AODST=0.0014*CAV*SQRT(CLAV)*81/PI
CIRCOT=2.0*PI*VTHEMO*AODST
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       BETA0=ATAN((1.-STHETA)*SEMT/SEMA)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      CLH=2.0 *SEMT*STHETA/(SEMR*SIGR)
                                                                                                                                                                                                                                                                                                                                                                                                                                              VTHEM0=0.5586 *WT00T * SQRT (CLAV)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 CIRCOH=FRLH*CLH/2. *CHORD*WT00T
                                                                                                                                                                                                                                                                                                                                                                                                   WT00T=SEMA/(SEMT*COS(BETA0))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(IPR.EQ.1) WRITE (16,1000)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  WT00T=SEMA/(SEMT*COS(BETA0))
                                                                                                                                                                                                        IF (ITPUTX.EQ.0) GO TO 100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF (IHBUTX.EQ.0) GO TO 300
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            OOT=CIRCOT/(AODST*2.*PI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     OOH=CIRCOH/(AODSH*2.*PI)
                                                                                                                                                                                                                                                                                                                                                                                                                           SEMR=SEMA/COS (ALPHR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SEMR=SEMA/COS (ALPHR)
                                                                                                                                                                                 FNBLAD=FLOAT (NBLADE)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           STHETA = SSTHET (NSTR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  SEMT = SSEMT (NSTR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       SAODS(1)=AODST
SCIRCO(1)=CIRCOT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     SVSDV0(1)=VSDV0T
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                SIGR = SSIGR (NSTR)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       SEMA=SSEMA (NSTR)
                                                                                                                                                           PIE4.0.ATAN(1.)
                                                                                                                                                                                                                                                                                            STHETA=STHETAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            AODSH=0.2*SIGR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SCIRCO(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               SVSDV0(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  SFRL(1)=FRLT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SAODS (1)=0.0
                                                                                                                                                                                                                                                                                                                                                          ALPHR=BETA0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SFRL(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           ALPHR-BETAO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    S00(1)=00T
                                                                                                                                                                                                                                                 SIGR=SIGIT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    VSDV0T=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               SCL(1)=CLT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            500(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      SCL(1)=0.0
                                                                       SFRL(2)
                                                                                                                                                                                                                                                                      SEMA-SEMAT
                                                                                                                                                                                                                                                                                                                   SEMT = SEMTT
                                                                                                                                                                                                                                                                                                                                                                                CHORD=SIGR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  CHORD-SIGR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          VSDV0H=0.2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        GO TO 200
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           FRLH=0.2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               C
100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     C
200
```

DUB0: (CHARLOTTE)RWTVM.FOR; 6

SAODS(2)=AODSH SCIRCU(2)=CIRCOH SOO(2)=00H SVSDV0(2)=VSDV0H

```
SUBROUTINE VORTX2 (IS,N,SIGIT,SEMAT,STHETAT,SEMTT,SIGI)
COMMON /FANVTX/ NSTR,SSIGR(51),SSEMA(51),SSTHET(51),SSEMT(51)
COMMON /VTEX1/ ITPVTX,IHBVTX,TAU,ALPHR,CHORD,WT00,B1
COMMON /VTEX2/ SAODS(2),SCIRC0(2),SO0(2),SVSDV0(2),SCL(2),
                                                                                                                                                                                                                                                                                                                                                                                 COMMON / VIEX3/ SBN(2), SBIST, RAWDS, R, VINRVT(300,2), I VISRVT(300,2), HTR, VINRV(300), VISRV(300)
COMMON / VIEX4/ CLAV, CAV, WT00T, ABR(51), CI, TVTI
COMMON/PRINTD/ IPRT, IPR
                                                                                                                                                                                                      C SUBROUTINE VORTX2 COMPUTES THE VELOCITY FIELD INDUCED BY C TIP AND HUB VORTICES AT ALL RADIAL LOCATIONS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF (ITPVTX.EQ.O.OR.IHBVTX.EQ.0) GO TO 100
                                                                                                                                                                        --- VORTX2-
FORMAT(//5x,'NO TIP VORTEX')
FORMAT(//5x,'NO HUB VORTEX')
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             SYO(2)=RAWDS-HTR*B1/(2.*PI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    IF (ITPUTX.EQ.0) GO TO 110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                DIMENSION ANE(300), SYO(2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            FNBLAD=FLOAT (NBLADE)
                                                                                                       OF SUBROUTINE VORTX1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              PI=4.0 * ATAN(1.0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SYO(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              SYO(1)=0.0
                                                                                                                                                                                                                                                                                                                                                                       SFRL(2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         GO TO 200
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   FNBLAD=B1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   NVORTX=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   NVORTX = 2
                                                                RETURN
                                                                                                             CEND
   1000
                        1100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 C
100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                υ
                                                                                                                                                                            ů
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   υv
                                                                                         U
```

IF(IPR.EQ.1) WRITE (16,1100)

SFRL(2)=0.0

SCL(2)=0.0

C FORMAT STATEMENTS

CONTINUE

C 400

SCIRCO(2)=0.0 SOO(2)=0.0 SVSDV0(2)=0.0

SAODS(2)=0.0

SFRL(2)=FRLH

GO TO 400

SCL(2)=CLH

SYO(2)=0.0

GO TO 200

Ü

## ORIGINAL PAGE IS

```
VTHEM=(0.024*SDISTV+0.5586)/(0.0504*SDISTV+1.0)*
                                                                                                                                                                                                                                                                                                                                                                SDISTV=SDIST*CHORD/(CAV*BL/PI)
A=(0.01584*SDISTV+0.0014)/(0.184*SDISTV+1.0)*
1 CAV*SQRT(CLAV)*B1/P1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               IF (ITPVTX.EQ.1.AND.IHBVTX.EQ.1) GO TO 220
IF (ITPVTX.EQ.0) GO TO 210
ZQRT=SDIST*COS(ALPHR)*R*SIG1*2.*PI/B1
BRRT=TVTI*ZQRT/(16.0*ZQRT+1.0)
BR=BRRT*BI/(2.*PI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(IPR.EQ.1) WRITE (16,1000)
GO TO 250
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  SBK(1)=BR
IF(IPR:EQ.1) WRITE (16,1010)
GO TO 250
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               IF(IPH.EQ.1) WRITE (16,1010)
GO TO 250
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           IF(IPR. EQ. 1) WRITE (16, 1000)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             CIRC=CIRC/(1.+SDISTV)**0.25
SYO(1)=RAWDS-HTR*B1/(2.*PI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           IF (IVORTX.EQ.1) GO TO 230
                                                                                                                                                                                                    DO 500 IVORTX=1, NVORTX
                                                                                                                                                                                                                                        CIRCU = SCIRCO (IVORTX)
                                                                                                                                                                                                                                                                          VSDV0 = SVSDV0 (IVORTX)
                                                                                                                                                                                                                                                                                                                                                                                                                                                        CIRC=2.0.PI.VTHEM.A
                                                      SCIRCO(1)=SCIRCO(2)
                                                                                        SVSDV0(1)=SVSDV0(2)
                                                                                                                                                                                                                       AODS = SAODS (IVORTX)
                                                                                                                                                                                                                                                                                                                                                                                                                                      1 WTOUT * SQRT (CLAV)
                                   SAUDS (1)=SAODS(2)
                                                                                                                                                                                                                                                                                                             FRL=SFRL(IVORTX)
                                                                                                                           SFRL(1)=SFRL(2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         BR=BR+TAU*SIG1T
                                                                                                                                                                                                                                                         00 = 500 (IVORTX)
                                                                                                                                                                                                                                                                                                                            BN=SBN(IVORTX)
                                                                                                                                                                                                                                                                                           CL=SCL(IVORTX)
                                                                                                                                                                                                                                                                                                                                             YO=SYO(IVORTX)
                                                                       500(1)=500(2)
                                                                                                        SCL(1)=SCL(2)
                                                                                                                                               SBN(1)=SBN(2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       BR=A+TAU*SIGR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             CIRC=CI*CIRC
                    SYO(2)=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                VSDV=VSDV0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   SBR(1)=BR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              SBR(1)=BR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SBR (2) - BR
                                                                                                                                                                                   CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  BR=YO-A
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                BR=YO-A
                                                                                                                                                                C
200
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 C
210
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          C
220
110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      c
230
```

WRITE (16,1160) VSDV WRITE (16,1170) CIRCO WRITE (16,1150) VSDV0

WRITE (16,1130) AODS WRITE (16,1140) A

IF (IPR.EQ.1) THEN

CIRCACIRCO VSDV=VSDVO

250 C C

CONTINUE

DUB0: [CHARLOTTE]RWTVM.FOR; 6

WRITE (16,1180) CIRC

WRITE (16,1200) BN WRITE (16,1210) BRRT

END IF

ANL(I)=ANL(I-I)+SANL

CONTINUE

300 C

DO 300 I=2,N

SANL=1 . RNI RN=FLOAT (N)

ANE(1)=0.0 RNI-RN-1.0

ARL=RAWDS \* (1.-R)

```
D1=COSH(VM)-COS(XN)
D2=COSH(VNN)-COS(XN)
VINRUT(I,IVORTX)=-CIRC/2.0*(SINH(VM)/D1-SINH(VNN)/D2)
VINRUT(I,IVORTX)=-VINRUT(I,IVORTX)*SEMTT/SEMT
                                                                                                C FORCED VORTEX NORMAL VELOCITY CALCULATIOIN
                                                                                                                                                  IF (RNVL.GT.RAL) RNVL=RAL
                                                                                                                                                                                                                           IF (ARL.GT.BR) Y1=Y0+BR
IF (ARL.LE.BR) Y1=BR-Y0
                                                                                                                                                                   THETAV=ACOS (RNVL/RAL)
                                                                                                                                                                                                                                                                                                                          VNN=2.*PI*(X1-Y0+BR)
XN=2.*PI*(X1-BN)
                                                                                                                                                                                                                                                                                                                                                                D1 = COSH (VM) - COS (XN)
                                                                                                                                                                                                                                                                                                        VM=2.*PI*(Y1-Y0-BR)
                                                                                                                                                                                     X0=A COS (THETAV)
                                                                                                                                                                                                           YO=A * SIN (THETAV)
                                                                              GO TO 410
                                                                                                                                                                                                                                                                       X1=BN-X0
                                                                                                                                                          400
                                                                                                                                                                                                                                                                                             U
```

ORIGINAL PAGE IS

OF POOR QUALITY

FREE VORTEX NORMAL VELOCITY CALCULATION

VM=2.\*PI\*(ARL-YO-BR) VNH=2.\*PI\*(ARL-YO+BR) XN=2.\*PI\*(ANL(I)-BN)

DUB0: [CHARLOTTE]RWTVM.FOR; 6

```
SPECIFIC HEAT RATIO CALCULATION FOR AIR AT LOW PRESSURES
                                                                                                                                                       PP=-0.093*((RAL/A)**2)
IF (PP.LT.-40.) PP=-40.
VISRUT(I,IVORTX)=-VSDV*EXP(PP)
VISRUT(I,IVORTX)=VISRUT(I,IVORTX)*SEMTT/SEMT
                                                         VINRVT(I, IVORTX) = VINRVT(I, IVORTX) * SEMTT/SEMT
D2=COSH(VNN)-COS(XN)
VINPRF=-CIRC/2.0*(SINH(VM)/D1-SINH(VNN)/D2)
VINRVT(I,IVORTX)=(RAL/A)*VINPRF
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         FORMAT (5X, 'AO/S', 6X, '=', F8.4)
FORMAT (5X, 'A/S', 9X, '=', F8.4)
FORMAT (5X, 'VSDVO,U', 5X, '=', F8.4)
FORMAT (5X, 'VSDV/U', 6X, '=', F8.4)
FORMAT (5X, 'CIRCO/(S*U)', 1X, '=', F8.4)
FORMAT (5X, 'CIR/(S*U)', 3X, '=', F8.4)
FORMAT (5X, 'RRT', 10X, '=', F8.4)
FORMAT (5X, 'BRT', 10X, '=', F8.4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            GAMMA=1.398 - 0.000043333*(TAMB - 200.0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      FROM KEENAN AND KAYE GAS TABLES
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           (///2x,'TIP VORTEX PARAMETERS')
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             (///2x,'HUB VORTEX PARAMETERS')
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(TAMB.LT.TC) RETURN
IF(TAMB.GT.200.0) GO TO 1
GAMMA=1.402 - 0.000017778*(TAMB+25.0)
                                                                                                                                                                                                                                                                                                                Do 510 I=1,N
Do 510 IVORTX=1,NVORTX
VINRV(I)=VINRV(I)+VINRVT(I,IVORTX)
VISRV(I)=VISRV(I)+VISRVT(I,IVORTX)
                                                                               C VORTEX STREAMWISE VELOCITY CALCULATION
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SUBROUTINE GAMCAL (TAMB, GAMMA)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   -** SUBROUTINE GAMCAL -----*
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 C END OF SUBROUTINE VORTX2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        GAMMA=1.402
                                                                                                                                                                                                                                                                                                                                                                                                                                    C FORMAT STATEMENTS
                                                                                                                                                                                                                                                          CONTINUE
                                                                                                                                                                                                                                                                           CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          CONTINUE
                                                                                                                                        CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                              CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       TC=-25.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             FORMAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             FORMAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   1150
1160
1170
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1200
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         1000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             1010
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                1130
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  1140
                                                                                                                                        110
                                                                                                                                                                                                                                                       120
500
C
                                                                                                                                                                                                                                                                                                                                                                                              510
                                                                                                                                                                                                                                                                                                                                                                                                                   U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        υv
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      U
```

DUB0: (CHARLOTTE | RWTVM. FOR; 6

\*\* SUBROUTINE PITCHI ---00000000

```
PITCH ANGLE CHANGE RELATIVE TO 'DESIGN' SETTING
--- ALSO CALCULATE FACE ALIGNMENT (FA) AND MID-CHORD
ALIGNMENT (MCA) ---
CALCULATE BLADE COORDINATE CHANGES DUE TO
```

SUBROUTINE PITCHI

```
COMMUN.COM12/ NZ, DTR.RTD, VO, CO, SXOCH(51)

COMMON > BLADEL/ THETA1(51), SIGR1(51), DPINT1(51),

1 CHORD1(51), TMOC1(51), ALPHA1(51),

1 Z1(51), ZMC1(51), YMC1(51),

1 BETAP1(51), MCA1(51), FA1(51),
                                                                                                           FA1(51),
SCD1(51),
                                                                                                                                          BETPP1(51), DELBP1
```

REAL MCAI

υv

υυ

DELBFIR=DTR\*DELBP1 PI=3.1415926

DO 10 I=1,NZ

DZ=0.5\*CHORD1(I)\*SIN(DTR\*BETAPL(I)) DY=0.5\*CHORD1(I)\*COS(DTR\*BETAPL(I)) ZTE=ZMC1(I)+DZ YLE=YMC1(I)-DY 2 LE = 2MC1 (I) -DZ YTE=YMC1(I)+DY

ORIGINAL PAGE

OF POOR QUALITY

IS

RMC=SQRT(ZMC1(I)\*\*2+YMC1(I)\*\*2) RLE=SQRT(ZLE\*ZLE+YLE\*YLE) RTE=SQRT(ZTE\*ZTE+YTE\*YTE)

IF(ZMC1(I).EQ.0.0) GO TO 20 PMC=ATAN2(YMC1(I),ZMC1(I)) GO TO 30 CONTINUE PMC=0.0

20

Ü

U

IF(YMC1(I).LT.0.0) PMC=-0.5\*PI IF(YMC1(I).GT.0.0) PMC= 0.5\*PI IF(2LE.EQ.0.0) GO TO 40 PLE=ATAN2(YLE, ZLE) GO TO 50 CONTINUE

40 30

CONTINUE

PLE=0.0

IF(TLE.LT.0.0) PLE=-0.5\*PI IF(YLE.GT.0.0) PLE= 0.5\*PI

IF(ZTE.EQ.0.0) GO TO 60

CONTINUE

20

91

υU U

DUB0: [CHARLOTTE]RWTVM.FOR; 6

PTE-ATAN2 (YTE, ZTE)

```
PITCH ANGLE CHANGE RELATIVE TO 'DESIGN' SETTING
--- ALSO CALCULATE FACE ALLIGNHENT (FA) AND MID-CHORD
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               COMMON/BLADE2/ THETA2(51), SIGR2(51), DPINT2(51),
1 CHORD2(51), TMOC2(51), ALPHA2(51),
1 22(51), ZMC2(51), YMC2(51),
1 BETAP2(51), MCA2(51), FA2(51),
1 BETAP2(51), DELBP2, SCD2(51),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                COMMON/COM12/ NZ, DTR, RTD, VO, CO, SXOCH(51)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             CALCULATE BLADE COORDINATE CHANGES DUE TO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   FA1(I) = ZMCP*COSBPP - YMCP*SINBPP
MCA1(I) = ZMCP*SINBPP + YMCP*COSBPP
                                                                                                                                                                                                                                                                                                                                                                                                                BETPP1(I)=0.0
IF(TOP.LT.0.0) BETPP1(I)=-0.5*PI
IF(TOP.GT.0.0) BETPP1(I)= 0.5*PI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           -** SUBROUTINE PITCH2 ----**
                                                  IF(XTE.LT.0.0) PTE=-0.5*PI
                                                                   IF(YTE.GT.0.0) PTE= 0.5*PI
                                                                                                                                                                                                                                                                                                                                               IF(BOT.EQ.0.0) GO TO 80
BETPP1(I)=ATAN2(TOP,BOT)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       BETPP1(I)=RTD*BETPP1(I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               ALLIGNMENT (MCA) ---
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     COSBPP=COS (BETPP1(I))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     SINBPP-SIN (BETPP1(I))
                                                                                                                                                                      YMCP=RMC*SIN(PPLE)
YLEP=RLE*SIN(PPLE)
YTEP=RTE*SIN(PPTE)
                                                                                                                                                                                                                                            ZMCP=RMC*COS(PPMC)
                                                                                                                                                                                                                                                             ZLEP-RLE * COS (PPLE)
                                                                                                                                                                                                                                                                              ZTEP=RTE * COS (PPTE)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SUBROUTINE PITCH2
                                                                                                                                                                                                                                                                                                                TOP = 2TEP - ZLEP
                                                                                                     PPMC=PMC-DELBP1R
PPLE=PLE-DELBP1R
                                                                                                                                        PPTE .. PTE - DELBPIR
                                                                                                                                                                                                                                                                                                                            BOT = YTEP-YLEP
GO TO 70
                                                                                                                                                                                                                                                                                                                                                                                 GO TO 90
                                                                                                                                                                                                                                                                                                                                                                                                                                                                     CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         CONTINUE
                                                                                        CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                 CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       EMT 2
                                      PTE-0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      RETURN
End
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         C C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                     90
0
                      9
                                                                                      7.0
                                                                                                                                                                                                                                                                                                                                                                                                   8
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            0 0 0 0 0 0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   O
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     U
                                                                                                                                                                                                                                                                                                U
                                                                                                                                                          U
                                                                                                                                                                                                                            Ų
```

c - 2

\_DUB0:[CHARLOTTE]RWTVM.FOR;6

υU

```
DZ=0.5*CHORD2(I)*SIN(DTR*BETAP2(I))
DX=0.5*CHORD2(I)*COS(DTR*BETAP2(I))
                                                                                                                                                                                                                            RLESQRT(ZLE*ZLE+YLE*YLE)
RMC=SQRT(ZMC2(I)**2+YMC2(I)**2)
RTE=SQRT(ZTE*ZTE+YTE*YTE)
                                                                                                                                                                                                                                                                                                                                                           IF(YMC2(I).LT.0.0) PMC=-0.5*PI
IF(YMC2(I).GT.0.0) PMC= 0.5*PI
                                                                                                                                                                                                                                                                                    IF(ZMC2(I).EQ.0.0) GO TO 20
PMC=ATAN2(XMC2(I),ZMC2(I))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF(YLE.LT.0.0) PLE=-0.5*PI
IF(YLE.GT.0.0) PLE= 0.5*PI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         IF(YTE.LT.0.0) PTE=-0.5*PI
IF(YTE.GT.0.0) PTE= 0.5*PI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    IF(ZTE.EQ.0.0) GO TO 60
PTE=ATAN2(XTE,ZTE)
                                                                                                                                                                                                                                                                                                                                                                                                  IF(ZLE.EQ.0.0) GO TO 40 PLE=ATAN2(YLE,ZLE)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              YMCP=RMC*SIN(PPHC)
YLEP=RLE*SIN(PPLE)
YTEP=RTE*SIN(PPTE)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    SIEP=KLE*COS(PPLE)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        ZMCP=RMC*COS (PPMC)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    ZTEP=HTE * COS (PPTE)
                                                      DELBP2R=DTR*DELBP2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       PPMC=PMC-DELBP2R
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 PPLE=PLE-DELBP2R
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  PPTE=PTE-DELBP2R
                                                                                                                                                                     ZTE=ZMC2(I)+DZ
YLE=YMC2(I)-DY
YTE=YMC2(I)+DX
                                                                                                                                                          ZLE=ZMC2(I)-DZ
                                                                                                 DO 10 I=1,NZ
                                       PI=3.1415926
REAL MCA2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                   GO TO 50
                                                                                                                                                                                                                                                                                                                                                                                                                                                 CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  GO TO 70
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               CONTINUE
                                                                                                                                                                                                                                                                                                                   GO TO 30
                                                                                                                                                                                                                                                                                                                                 CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                               PLE=0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               PTE = 0.0
                                                                                                                                                                                                                                                                                                                                               PMC=0.0
                                                                                                                                                                                                                                                                                                                                                                          ្គ
93
                                                                                                                                                                                                                                                                                                                                                                                                                                                 0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         5.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  9
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        7.0
                                                                                                                                                                                                                                                                                                                                  20
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    U
             O O
                                                                      υU
                                                                                                                                                                                                                   U
                                                                                                                                                                                                                                                                           U
```

```
DUB0: [CHARLOTTE]RWTVM.FOR; 6
```

```
DIMENSION AAA(10)
DIMENSION X(10), Y(10), XC(10), YC(10)
NOTE. THE DIMENSION @10@ DOES NOT NEED TO AGREE WITH THE CALLING PROGRAM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           FOR INTERPOLATION
                                                                                                                                                                                                                                                                                                                                          INTEGRATE OR INTERPOLATE USING A PARABOLA WHICH PASSED THROUGH THE ITH
                                                                                                                                                                                                                                                                                                                                                   EXIST) SUCH THAT THE SQUARE OF THE DEVIATION IS A MINIMUM. NOTE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  YC(IC) = INTEGRAL(Y*DX) FROM XC(I) TO XC(IC) WHERE IC=2,NXC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             =1 TO GET 1ST DERIVATIVE,
                                                                                                                                                                                                                                                                                                                                                                                                                                                      SUBROUTINE LSPFIT (X, Y, NPTS, XC, YC, NXC, ND, AAA)
                                                                                                                                                                                                                                                                                                                                                                                                                            Y-Y(I) = B^*(X-X(I)) + C^*(X-X(I))^{**}2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     LIST OF X AT WHICH CALC TO BE DONE
                                                                                                                                                                                                                                                                                                                                                                                  THAT I IS GENERALLY SELECTED SUCH THAT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      COORDINATE OR DERIVATIVE AT XC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    ND = -1
                                                                                                                                                                                  FA2(I) = ZMCP*COSBPP - YMCP*SINBPP
MCA2(I) = ZMCP*SINBPP + YMCP*COSBPP
                                                                                             IF(TOP.LT.0.0) BETPP2(I)=-0.5*PI
IF(TOP.GT.0.0) BETPP2(I)= 0.5*PI
                                                                                                                                                                                                                                                                                                                                                                                                X(I).LE.XC.LT.X(I+1)
THE EQUATION FOR THE PARABOLA IS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   INTEGRATION CONSTANT IF
                                                                                                                                                                                                                                                                                                               ** SUBROUTINE LSPFIT ----**
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         =-1 FOR INTEGRATION
                                         BETPP2(I)=ATAN2(TOP, BOT)
                                                                                                                                                                                                               BETPP2(I)=RTD*BETPP2(I)
                           IF (BUT. EQ. 0.0) GO TO 80
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             #0 TO GET COORD,
                                                                                                                                                        COSBPP=COS(BETPP2(I))
                                                                                                                                                                       SINBPP=SIN(BETPP2(I))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          PTS. ON CURVE
= 2TEP - ZLEP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      COMMON /CLSPF / I
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 NO. OF XC
              - YTEP-YLEP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         NO OF X
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    LOGICAL WITHIN
                                                                                  BETPP2(I)=0.0
                                                                                                                                                                                                                                           CONTINUE
                                                         GO TO 90
                                                                      CONTINUE
                                                                                                                              CONTINUE
                                                                                                                                                                                                                                                      RETURN
END
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    YC(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         OUTPUT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             INPUT-
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                NOTES-
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          X, Y
NPTS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 NXC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      XC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       Ϋ́С
                                                                                                                                                                                                                              C C
                                                                      80
                                                                                                                            90
                                                                                                                                                                                                                                                                                                                            0 0 0 0 0
                                                                                                                                                                                                                                                                                                                                                                                                 \circ \circ \circ \circ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 00000000000000000000
                                                                                                                                                                                                                                                                                                                                                                                           94
```

```
F.EQ.1.0, CHECK FOR INTEGRATION AND DOUBLE POINT BEFORE INCREMENTING IF ((ND.EQ.(-1)) .OR. (I.NE.N .AND. X(I+1).EQ.X(I+2))) GO TO 120
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         PRELIMINARY CALCULATIONS FOR INTERPOLATION OR INTEGRATION
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   TOP = X1*(Y3*XI-(Y(I-1)-YI)*X3)*X13

BOT = X1*XI*X13*X13*X3

IF(I.GE.N.OR. (XD.EQ.0. AND. BOT.NE.0.)) GO TO 128

X4 = X(I+2)-XI
                                                                                                                                                                                                                                                                                 F.LT.0. (F IS THE FRACTIONAL POSITION IN THE INTERVAL)
IF(I.EQ.1) GO TO 120
IF(ND.EQ.(-1)) GO TO 119
                                                                                                               BEGIN INTERPOLATION LOOP FOR XC(IC) IC=1,NXC
                                                                                                                                                                                                                                                                                                                                                                                                                                                   IF(SGN*(XC(IC)-X(I+1))) 120,112,114
                                                                                     = SIGN(1., X(N+1)-X(1))
                                                                                                                                                                                                                                                                                                                                                                                              IF (X(I+1).NE.XI) GO TO 120
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         IF(I.EQ.N) GO TO 120
IF(ND.EQ.(-1)) GO TO 122
                                         I = \text{MAXO(1,MINO(I,N))}
IF(ND,EQ.(-1)) I=I
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(I-ISAVE) 124,129,124
                                                                                                                                             LOCATE APPROPRIATE INTERVAL
                                                                                                                                                                                                                                                               IF(SGN.XD) 105,107,110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            = X(I-I)-X(I+I)
                                                                                                                                                                                     IF(NCOUNT) 119,103,103
NCOUNT= NCOUNT-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF(I.LE.1) GO TO 127
DUB0: [ CHARLOTTE | RWTVM. FOR; 6
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               = X(I-I)-XI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         = X(I+1)-XI= Y(I+1)-YI
                                                                                                                                                                                                                                   = xc(1c)-xi
                                                                                                                                                                                                                                                     IF(N) 104,120,104
                                                                                                                                                             WITHIN= .FALSE.
NCOUNT= N
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  WITHIN= . TRUE .
                              = NPTS-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            = X(I)
                                                                                                                                                                                                                         = x(I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           = I+1
                                                                                                                                                                                                                                                                                                                                          <u>- 1-1</u>
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               ISAVE = I
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          GO TO 102
                                                                                                                                                                                                                                                                                                                                                                                                                 911 CL 05
                                                                            0
                                                                                                                                                                                                                                                                                                                                                       GO TO 102
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                F.GT.1.0
                                                                                                                                                                                                                                                                                                                                                                                     F. EQ.0
                                                                                                                                                                                                                                                                                                                                                                                                                                              F.GT.0
                                                                             ISAVE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        TOP
                                                                                            SGR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              127
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          119
                                                                                                                                                                                                                                                                                                                                                                                                                                                             110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         C
112
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  114
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             116
                                                                                                                                                                                                                                                                                                                                                                                                   107
                                                                                                                                                                                                                                                                     104
C
C
105
                                                                                                                                                                   100
                                                                                                                                                                                                102
                                                                                                                                                                                                              103
                                                                                                                                                                                                                                                                                                                                                                                                                             ບ ບ
95
```

- C\*X3

B = 0. If (N.GT.0 .AND. X3.NE.0.) B = (Y(I+1)-YI)/X3If (ND) 130,140,141

IF ( . NOT . WITHIN ) XD=X3

130

ND=-1, INTEGRATE

129 C

TOP = TOP + X4\*(X3\*X4-(X(I+2)-YI)\*X3)\*X43 BOT = BOT + X4\*X4\*X43\*X3 IF(BOT:NE.0.) C = -TOP/BOT

= X(I+2)-X(I+1)

X43 TOP

128

### ORIGINAL PAGE IS OF POOR QUALITY

@IQ IS BEING INCREMENTED TO FIND APPROPRIATE INTERVAL.
CUMULATE THE INTEGRAL OF THE ITH INTERVAL.
SA = SA + S1
GO TO 116 X(I) - XC(IC) - X(I+1)IF(ND.NE.(-1).AND.XC(IC).EQ.XC(IC-1)) I=I+1 GO TO 100 S1 = (YI + (B/2, + C/3, \*XD) \*XD) \*XDIF (WITHIN) GO TO 135 ND=0, INTERPOLATE FOR COORDINATES YC(IC) = YI + (B + C\*XD)\*XD GO TO 150 APPROPRIATE INTERVAL FOUND.

IF (IC.EQ.1) SA=YC(IC)=S1

IF (IC.NE.1) YC(IC)=SA+S1

GO TO 150 IC = IC+1 AAA(IC-1)=2.\*C IF(NXC-IC) 900,160,160 ND=1, FIRST DERIVATIVE YC(IC) = B + 2.\*C\*XDGO TO 150 RETURN **1**C C 135 140 141 150 160 006

### C. Definition of Input/Output Parameters

This section of the appendix defines all input and output parameters of the Rotor Wake/Tip Vortex Model (RWTVM) computer program. The input is read into the computer program in terms of two input files, one for each rotor.

### Input Parameters

Input parameters are grouped under:

- a. Blade geometry
- b. Blade aerodynamic performance and ambient conditions
- c. Wake parameters (for forward rotor only)
- d. Tip vortex parameters (for forward rotor only)
- a. Blade Geometry Input Parameters
- BETAP Design or reference blade section pitch angle, degree; input one value for each streamline.
- BETA34 Pitch angle at 3/4 radius ratio  $(R/R_{\mbox{tip}})$  of the blade for a particular operating condition.
- CHORD Blade chord normalized by tip diameter, input one value for each streamline.
- DELBP Pitch angle change from design, degree

DT - Tip diameter, feet

HTR - Hub-to-tip radius ratio

NB - Number of rotor blades

NP - Number of propellers

NZ - Number of spanwise stations Maximum value = 10 = default value

Note: Streamline Number 1 should be the tip streamline.

TMOC - Maximum blade section thickness normalized by chord.
Input one value for each streamline.

XPCA - Distance between the pitch change axes normalized by front rotor tip diameter

YMC - Tangential location of blade midchord line relative to pitch change axis normalized by tip diameter at design pitch angle. Input one value for each streamline.

Z - Radius normalized by tip radius. Input one value for each streamline.

ZMC - Axial location of blade midchord line relative to pitch change axis, normalized by tip diameter, at design pitch angle. Input one value for each streamline.

### b. Blade Aerodynamic Performance and Ambient Input Parameters

ALPHA - Blade section angle of attack, degrees; input one value for each streamline.

NCASE - Number of cases
Default value = 1

PAMB - Ambient pressure (static pressure) in psi

RPM - RPM of the rotor (physical)

SHP - Shaft horsepower of the rotor (physical)

TAMB - Ambient temperature (static temperature) in ° F

VO - Flight speed, fps

### c. Wake Parameters

BETAW - Parameter to account for wake flow angle variation from freestream.

Default value = 0.0.

IRW - Option to compute wake/tip vortex gust field
 IRW = 0 - No
 IRW = 1 - Yes
 Default value = 1

NSTEP Number of points in the velocity profile across one blade spacing
Maximum value: NSTEP = 150

NWHM - Number of sequential harmonics required for Fourier
analysis.
Maximum value: NWHM = 21.

SCD - Local section drag coefficient.
Input one value for each streamline.

VREF - Reference velocity by which the gust upwash velocity
harmonic coefficients are normalized, fps
Default value: VREF = 10.0.

WTIV - Inviscid velocity gradient, normalized by wheel speed.

Default value: WTIV = 0.0.

### d. Tip Vortex Parameters

CI - Circulation index for tip vortex strength (see Eq. 13a).

Default value: 1.0.

IHBVTX - Option to include hub vortex
IHBVTX = 0 - No
IHBVTX = 1 - Yes
Default value: IHBVTX = 0

ITPVTX - Option to include tip vortex
ITPVTX = 0 - No
ITPVTX = 1 - Yes

PCTVTX - Percent outboard span whose circulation gets rolled up into tip vortex.

Default value: PCTVTX = 30.0.

- SBN(1) Tangential distance normalized by tip blade spacing for the tip vortex center (see Figure 2, b,).
- SBN(2) Tangential distance normalized by hub blade spacing for the hub vortex center.
- TAU Tip clearance normalized by the rotor chord at the tip.

  Default value: TAU = 10.0.
- TVTI Tip vortex trajectory index (see Eq. 19).

  Default value: TVTI = 2.0.

### Output Parameters

### Output parameters are grouped under:

- a. Blade parameters
- b. Wake parameters
- c. Tip vortex parameters
- d. Velocity profile parameters
- e. Gust spectral parameters

### a. Blade Parameters

- BETAP Pitch angle for the case under study, degrees
- CD Blade section drag coefficient
- CHORD Chord normalized by tip diameter
- CL Blade section lift coefficient
- FA Face alignment normalized by tip diameter
- MCA Midchord alignment normalized by tip diameter
- R/RT Radius normalized by tip radius
- SHP/AA Shaft Horsepower/(Annulus Area)
- SHP/D2 Shaft Horsepower/(Tip Diameter)<sup>2</sup>

### b. Wake Parameters

- CD Blade section drag coefficient
- SDIST Streamwise distance to 1/4 chord point of aft rotor from forward rotor trailing edge normalized by forward rotor chord.

WAKE - Semiwake width normalized by blade spacing WIDTH

WD/UT - Wake centerline defect normalized by local wheel speed

WFS/UT - Free-stream velocity normalized by local wheel speed

X/C - Axial distance to leading edge of aft rotor from trailing edge of forward rotor normalized by forward rotor chord

### c. Tip Vortex Parameters

- A/S Radius of the tip vortex core normalized by forward rotor tip spacing at the 1/4 chord point of the aft rotor.
- AO/S Radius of the tip vortex core normalized by forward rotor tip spacing at the trailing edge of forward rotor tip.
- BN Tangential location of the tip vortex normalized by tip blade spacing.
- BRRT Spanwise location of the tip vortex from the rotor tip normalized by tip radius.
- CIR/ Circulation of the tip vortex core at the 1/4 chord (S\*U) of aft rotor normalized by the product of forward rotor tip spacing and tip speed.
- CIRCO/ Circulation of the tip vortex core at the trailing (S\*U) edge of forward rotor tip normalized by the product of forward rotor tip spacing and tip speed.
- VSDV/U Streamline velocity defect of tip vortex core at 1/4 chord of aft rotor normalized by blade tip speed.
- VSDVO/U Streamwise velocity defect of tip vortex core at the trailing edge of forward rotor tip normalized by blade tip speed.

### d. Velocity Profile Parameters

- ALPHA Flow angle of the velocity vector relative to aft rotor to the axial flow direction, degrees
- I Index for tangential profile
- Tangential distance from wake centerline divided by blade spacing
- THETA Angular location relative to the wake centerline, degrees

- VN Normal (upwash) velocity relative to aft rotor divided by forward rotor wheel speed
- VS Streamwise velocity relative to aft rotor divided by forward rotor wheel speed
- VT Total (vector sum of VN and VS) velocity relative to aft rotor divided by forward rotor wheel speed
- VPN Normal (upwash) perturbation velocity from the free stream relative to aft rotor divided by forward rotor wheel speed. Fourier coefficients are evaluated for this profile.
- VPS Streamwise perturbation velocity from the free stream relative to aft rotor divided by forward rotor wheel speed.
- VPT Total (vector sum of VPN and VPS) perturbation velocity relative to aft rotor divided by forward rotor wheel speed
- WN Normal velocity relative to forward rotor divided by forward rotor wheel speed
- WS Streamwise velocity relative to forward rotor divided by forward rotor wheel speed
- WT Total (vector sum of WN and WS) velocity relative to forward rotor divided by forward rotor wheel speed

### e. Gust Spectral Parameters

AERO PHASE LAG - Phase lag relative to tip streamline, degrees

2\*CMOD - 2X amplitude of complex Fourier coefficient of upwash perturbation velocity divided by wheel speed (factor of 2 to take into account both positive and negative gust harmonic numbers)

20 % LOG - dB level of the (2%CMOD) of upwash perturbation (2XCMOD) velocity, VREF, defined by:

20 log (2\*CMOD\*WHEEL SPEED/VREF)

NH - Gust harmonic number

PHASE - Phase of the complex Fourier coefficient of upwash perturbation velocity, radian

### D. A Sample Input/Output Case

A sample input/output case enclosed in this section pertains to F7-A7 blade geometry at 80% design rpm in a 9x8 configuration at a flight Mach number of 0.25 (Test Point 3704). The axial distance between the pitch change axes equals 0.2408\*tip diameter of forward rotor. The spanwise variation is prescribed in terms of geometric and aerodynamic data at ten streamlines.

The input is prescribed in terms of two data files, one for forward rotor and another one for aft rotor.

```
T F73704V.DAT
$INFUT
NCASE=2
DT=2.05 HTR=0.428 NB=9
SHP=205.9 RPM=6722 DELBP=-18.529
VO=284.74 TAMB=48.65 PAMB=14.7 NF=1
XPCA=.2408 BETA34=41.8
MZ/Z=
1. .979 .9576 .9144 .8221 .7184 .594 .5189 .4762 .4279
ZMC=
.05978 .05538 .05012 .04047 .01881 -.00106 -.01271 -.01086
-.00674 .00092
YMC=
.06248 .05609 .04970 .03770 .01654 .00035 -.00568 -.00341
-.00035 .00248
CHORD=
.0327 .0561 .0703 .088 .1058 .1200 .1278 .1278 .1271 .126
[MOC=
.04 .025 .0218 .02 .023 .0299 .0462 .064 .0805 .1025
BETAR=
43.4 46.2 48 50.2 53.8 58.3 64.8 68.9 70.4 70.7
.0383 .056 .072 .097 .145 .202 .272 .3325 .381 .44
·冯上州·丹=
10*0.0
ISHAPE=2. BETAW=0.0. NWHM=10
VREF=10.0. NSTEF=101.IRW=1.IWAKE=2
IPRNIM=0. SCD=10*.015 WTIV=0.0
ITFVTX=1 IHBVTX=0 SBN=.5 0. FAU=10.0 CI=1.0 TVTI=2.0
```

### Input File for the Forward Rotor

ORIGINAL PAGE IS OF POOR QUALITY

```
5 T A73704.DAT
                                              WHOSENER PARTY IS
$ I NEUT
NCASE=2
                                              OF MER DURING
DT=2.00 HTR=0.4159 NB=8
SHP=208.3 RPM=6718 DELBP=-17.428
BETA34=41.4
NZ/Z=
1. .9776 .9554 .9105 .8015 .7105 .5845 .5078 .4644 .4159
ZMC=
.05442 .04931 .04565 .03616 .01351 -.00314 -.01665 -.01454
-.00877 -.00073
YMC=
.06574 .05917 .05340 .04127 .01812 .00365 -.00533 -.00373
-.00095 .00329
CHORD=
 .03433 .05771 .07378 .09167 .11103 .12345 .13149 .13141
 .13 .12856
TMOC=
 .04 .025 .0212 .021 .0238 .0298 .0471 .0662 .086 .1048
BETAF=
45.3 47.7 48.7 50.3 53.3 56 60.6 63.7 64.8 64.2
 THETA=
 .0383 .056 .072 .097 .145 .202 .272 .3325 .381 .44
ALPHA=
 10*0.0
```

### Input File for the Aft Rotor

### \*\*\*\* RWTUM \*\*\*\*

0

UDF ROTOR GUST PREDICTION PROGRAM

BETAP SURFACE APPROXIMATION MODEL

WAKE/VORTEX MODEL INCLUDED

FORWARD CHUDFILE IS F73704V.DAT

AFT CRUDFILE IS A73704.DAT

DATE; 6-NOV-87, TIME; 17:21:41

\*\*\* ROTOR 1 INPUT PARAMETERS - CASE NO. 1 \*\*\*

PROPELLER TIP DIAMETER DT = 2.0500 FT.

NUMBER OF BLADES NB = 9

SHAFT HORSEPOWER SHP = 205.90

ROTATIVE SPEED (RPM) = 6722.0

FLIGHT VELOCITY VO (FPS) = 284.74

AMBIENT TEMPERATURE TAMB = 48.65 DEG. F

AMBIENT PRESSURE PAMB = 14.700 PSIA

NUMBER OF PROPELLERS NP = 1

\*\*\* ROTOR 2 INPUT PARAMETERS - CASE NO. 1 \*\*\*

PROPELLER TIP DIAMETER DT = 2.0000 FT.

NUMBER OF BLADES NB = 8

SHAFT HORSEPOWER SHP = 208.30

ROTATIVE SPEED (RPH) = 6718.0

FLIGHT VELOCITY VO (FPS) = 284.74

AMBIENT TEMPERATURE TAMB = 48.65 DEG. F

AMBIENT PRESSURE PAMB = 14.700 PSIA

DUB0: [CHARLOTTE.NASA.CRUDFAN]73704V.PRN;1

NUMBER OF PROPELLERS NP =

```
XPCA = 0.2408

IRW = 1

IWAKE = 2

TIP SPEED MACH NO. = 0.6527

FLIGHT MACH NO. = 0.2576

HELICAL MACH NO. = 0.7017

TIP SPEED MACH NO. = 0.7017

HELICAL MACH NO. = 0.556

HELICAL MACH NO. = 0.6865
```

		TABLE OF	BLADE	TABLE OF BLADE SECTION PROPERTIES - ROTOR	PROPERTI	ES - ROT	0R 1			
SECTION	R/RT	CHORD	TM/C	АГРНА	BETAP	MCA	FA	CL	9	
						4	3000	9500	0.015.0	
-	1.0000		0.0400			0.000	0000.0			
, ~	0.67.0		0.0250			0.0788	7700.0-	0.6263	0010.0	
4 ^	46.00		0.0218			0.0705	-0.0034	0.8287	0 . 0 1 5 0	
n ·	0.00		0000			0.0552	-0.0031	0.8457	0.0150	
4	7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7		9 6			0.0249	-0.0022	0.9282	0.0150	
Ŋ	0.8221		0.0230				5000	9896	0.0150	
•	0.7184		0.0299	00.0		000.0-	1000 0 0010 0 Jt 01	0 9633	0.510 0	
7	0.5940		0.0462			ec 10.0-		1000	0.00	
90	0.5189		0.0640			-0.0114	/ 000 0-		0110	
o	0.4762		0.0805			-0.0065	-0.0019		0.10.0	
10	0.4279	0.1260	0.1025			0.0017	-0.0020	1.0038	0 . 0 1 0 . 0	

TABLE OF BLADE SECTION PROPERTIES - ROTOR 2	ALPHA BETAP MCA FA CL	0.00 31.92 0.0849 -0.0084 1.1659 0.00 34.32 0.0763 -0.0106 0.9693 0.00 35.32 0.0695 -0.0100 0.9335 0.00 39.92 0.0542 -0.0087 0.9336 0.00 42.62 -0.0006 -0.0048 0.9468 0.00 47.22 -0.0171 -0.0035 0.9268 0.00 50.32 -0.0147 -0.0035 0.9268 0.00 50.32 -0.0147 -0.0033 0.9258
BLADE SECTI	TM/C ALE	0.0400 0.0250 0.0212 0.0212 0.0218 0.0238 0.0298 0.0471 0.0662 0.0662
TABLE OF	CHORD	0.0343 0.0577 0.0917 0.1110 0.1235 0.1315
	R/RT	1.0000 0.9776 0.98584 0.9105 0.8015 0.7105 0.5845
	SECTION	<b>よるままららてきの</b> 。

ROTOR 1

EFFECTIVE AERO SHP = 205.90
ROTOR ANNULUS AREA = 2.696 SQ FT
DISK LOADING SHP/D2 = 48.99
DISK LOADING SHP/AA = 76.37

107

# DUB0: { CHARLOTTE: NASA. CRUDFAN | 73704V. PRN; 1

POWER COEFFICIENT CP=

0.917

ROTOR 2

EFFECTIVE AERO SHP = 208.30
ROTOR ANNULUS AREA = 2.598 SQ FT
DISK LOADING SHP/D2 = 52.08
DISK LOADING SHP/AA = 80.17
POWER COEFFICIENT CP= 1.051

ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER 1 ---

CD = 0.0150

00 80 NO HUB VORTEX WFS/UT = 1.0286 WD/UT = 0.0082 X/C = 6.7121 SDIST = 18.1786 WAKE WIDTH = 0.0871 TIP VORTEX PARAMETERS

A0/5 = 0.0003

A/5 = 0.0101

VSDV/V = 0.0000

CIRCO/(5\*U) = 0.0009

CIR(5\*U) = 0.0186

BN = 0.5000

BRRT = 0.1099

# HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

, DB					
20 * LOG ( 2 * CMOD)	-	•	-45.18	~23.50	-30.03
PHASE	0.000000	-0.000022	-0.001055	-0.000096	-0.000192
2 * CMOD	0.004165	0.002783			0.000437
H	-	7	~	4	2

-29.81	~	36.	39.	43.
000.0	-0.000133	000.0	000.	000
0004	0.000289	0000	000	0000
٥	7	29	ð	10

### ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER 2

```
1.0106
0.0148
3.6532
9.8043
CD = 0.0150
WES/UT #
X/C
SDIST #
WAKE WIDTH #
```

TIP VORTEX PARAMETERS

A0/S

A/S

10.000

VSDV0/U

CIRCO/(S\*U) = 0.016

BN

BRRT

10.000

109

HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

7	2 · CMOD	PHASE	20 * LOG (2 * CMOD), DB
-	0 008634	0.00000	-4.30
• ~	00	900000.0	-7.05
, m	0000	0.000127	-33.58
		0.000026	-17.11
٠.	0.000531	-0.000056	-28.51
9		0.000038	-25.93
j		0.000035	-33.61
· 00	00023	-0.000066	-35.71
5		0.000208	-43.14
10	090000.0	-0.000792	-47.44

## ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER 3

0.9951 0.0192 2.7973 7.3895 0.1161 SDIST \*\* WAKE WIDTH \*\* CD = 0.0150WFS/UT WD/UT **X**/C

TIP VORTEX PARAMETERS
A0/5 \* 0.00

0.0003 0.0065 0.0000 0.0000 0.0009 0.0149 n 11 14 11 11 CIRC0/(S\*U) A/S VSDV0/U n/ndsn

0.1091 CIR/(S\*U) BRRT HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

**8**0 20 \* LOG ( 2 \* CMOD ) , -0.15 -1.8.50 -1.2.74 -4.0.88 -22.35 -40.23 -33.14 -52.91 0.000011 0.000212 -0.00044 -0.000362 PHASE 0.000001 0.000003 0.000019 0.000009 2 \* CMOD 0 . 014223 0 . 010431 0 . 001720 0 . 0013138 0 . 00011104 0 . 0000131 0 . 0000333 

ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

STREAMLINE NUMBER

2.0945 5.3166 0.1211 0.9739 0.0257 SDIST = WAKE WIDTH = ŧ CD = 0.0150WFS/UT WD/UT SDIST X/C

```
0.1086
                                                                                                    0.0003
0.0053
0.0000
0.0000
0.0009
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      0.5000
TIP VORTEX PARAMETERS
                                                                                                                                                                                                                            A/S
VSDV0.U = VSDV/U = CIRCO/(S*U) = CIRCO/(
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            CIR/(S*U)
BN
BRRT
                                                                                                                                                      A0/5
```

HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

<b>X</b>	2 • CMOD	PHASE	20 * LOG ( 2 * CMOD),
-	0.021909	0.00001	3.20
. ~		0.000004	1.69
, ~	0.006762	0.00000.0	-7.01
7	0.008444	0.00000	
ď	0.003373	-0.00000-	1
•	0.004304	0.000015	1
_	0.002292	-0.000023	-16.
- 00		0.000028	-16.
5	0.001608	0.000045	-19.48
9	0 001410	0.000025	-20.63

ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

```
--- STREAMLINE NUMBER 5
                       0.9417
0.0354
1.5860
3.6393
0.1173
                CD = 0.0150
WFS/UT
                                         X/C
SDIST
                                TU/QW
```

WAKE WIDTH =

```
0.1078
     0.0003
0.0041
0.0000
0.0000
0.0107
0.5000
TIP VORTEX PARAMETERS
      A0/S
A/S
VSDV0/U
CIRCO/(S*U) =
CIR/(S*U) =
                                                     BRRT
```

# HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

20 * LOG (2 * CMOD), DB	-2.67	~0.41	-15.26	-6.30	-20.07	-11.99	-20.65	-17.54	-22.27	-22.38
PHASE	0.00000	0.00000.0	0.000013	-0.00001	0.000004	-0.00000	-0.000022	0.000020	0.000033	0.000049
2.CMOD	0.012393	0.016077	0.002908	0.008159	0.001673	0.004238	0.001564	0.002238	0.001298	0.001282
X	-	7	•	7	S	٥	7	20	5	10

### ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER 6 ---

CD = 0.0150
WFS/UT = 0.9181
X WD/UT = 0.0467
X X X = 1.3019
SDIST = 2.6103
WAKE WIDTH = 0.1107

TIP VORTEX FARAMETERS

A0/S = 0.0003

A/S = 0.0032

VSDVO/U = 0.0000

CIRCO/(S'U) = 0.0009

CIR/(S'U) = 0.0088

BN = 0.5000

BRRT = 0.1071

# HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

E 20 LOG (2 CMOD),	01 -11.38		000013 -33.56	8.9-	0047 -38.06	00008 -12.52	59 08- 1500
PHAS	0.0000	00.0	-0.00	•	00.0	0.00	
2.CMOD	0.005206	0.016019	0.000405	٠.	0.000241	0.004564	0.000566
X	-	7	m	4	'n	9	7

DUB0: [CHARLOTTE.NASA.CRUDFAN]73704V.PRN:1

-18.6	-27.3	-24.3
.0000.	0.000062	00000
.0022	0.000826	.0011
æ	3	10

### ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER 7 ---

	.925	.062	. 104	1.9022	. 102
20	îŧ	11	11	11	H
0.01	WFS/UT	WD/UT	x/c	SDIST	WAKE WIDTH

### TI

RAMETERS	<b>= 0.0003</b>	= 0.002	0.000.0	0.000	000.00 = (1	= 0.007	= 0.500	1 0 1
IP VORTEX PA		s/	Ď	n/nas	IRC0/(5	IR/(S*1	BN	#00B

# HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

H	2 * CMOD	PHASE	္
-	0.003537	0.00000	-16.39
. ~		0.00000	-3.39
m	0.005395	0.00000	-12.
4	0.009626	0.000004	-7.
·v	0.003374	0.00000	-16
• •	0.005142	0.00007	-13.14
7	0.001229	0.00000	-25.57
•	0.002388	900000.0	-19.80
o	0.000086	-0.000207	-48.63
10	0.001049	-0.000002	-26.95

## ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER

0.9473 0.0717 1.0682 1.6577 0.0984 9 9 H H CD = 0.0150SDIST WAKE WILTH WFS/UT WD/UT x/c

TIP VORTEX PARAMETERS

A0/S = 0.0003

A/S = 0.0023

VSDV/U = 0.0000

CIRCO/(S'U) = 0.0009

CIR/(S'U) = 0.0009

BN = 0.5000

BRRT = 0.1056

ROTOR WAKE/VORTEX FLOW HARMONIC CONTENT OF

08 20\*LOG(2\*CMOD), D -8.75 -5.11 -9.53 -8.74 -13.55 -13.95 -20.28 -20.28 -20.28 2 \* CMOD 0 009751 0 014830 0 008920 0 008920 0 005613 0 002587 0 002587 0 002587 12m4501001

ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER

0.9685 0.0768 1.0799 1.5685 0.0976 CD = 0.0150SDIST = MAKE WILTH = WFS/UT WD/UT X/C

TIP VORTEX PARAMETERS

AO / S = 0.0003

A/ S = 0.0022

VSDV0.U = 0.0000

CIRCO (S \* U) = 0.0009

CIR(S \* U) = 0.0064

BN = 0.5000

BRRT = 0.1056

HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

<b>m</b>										
20*LOG(2*CMOD), DB	·.	4.	•	٥		<b>~</b>	æ	•	۲. ع	-31.05
PHASE	0.00000.0	0.00000	0.00003	0.000004	0.00000.0	0.00000	0.00000	0.00007	0.00007	0.000012
7 CMOD	0.013721	0.013838	0.011076	0.009547	.00689	.00525	0.003339	0.002306	0.001251	0.000816
Z	1	7	~	7	· un	9	٢	•	σ.	10

ROTOR WAKE/VORTEX FLOW PROGRAM

CASE NUMBER

--- STREAMLINE NUMBER 10 ---

CD = 0.0150
WFS/UT = 1.0151
WD/UT = 0.0836
X/C = 1.0992
SDIST = 1.4986
WAKE WIDTH = 0.0993

TIP VORTEX PARAMETERS

A0.5 = 0.0003
A.S = 0.0021
VSDV.U = 0.0000
CIRCO/(S^U) = 0.0009
CIR/(S^U) = 0.0062
BN = 0.5000

DUBO: [CHAKLOTTE.NASA.CRUDFAN]73704V.PRN;1

HARMONIC CONTENT OF ROTOR WAKE/VORTEX FLOW

DB										
20 * LOG ( 2 * CMOD),	-4.79	80.8-	-7.47	-10.95	-11.87	-16.40	-18.13	-24.39	-26.13	-35.59
PHASE	0.00000.0	0.00003	0.000003	0.00000.0	900000.0	0.00000	0.00000.0	0.00000	0.000013	600000.0
2.CMOD	0.018663	0.012771	0.013700	0.009182	0.008259	0.004905	0.004017	0.001954	0.001599	0.000538
ΞZ	7	7	~	47	2	9	7	80	9	10

LAG, DEG.										
NO. AERO PHASE	0.00000.0	-5.232219	-9.057590	-15.719318	-27.892509	-38.541042	-49.121807	-52.943192	-53.98853	-54.526115
STREAMLINE		7	3	7	S	٥	7	89	6	0.1
	NO. AERO PHASE	NO. AERO PHASE 0.000000	NO. AERO PHASE 0.000000 -5.232219	NO. AERO PHASE 0.000000 -5.232219 -9.057590	NO. AERO PHASE 0.000000 -5.232219 -9.057590 -15.719318	NO. 0.00000 0.000000 -5.232219 -9.057590 -15.719318	NO. 0.00000 0.000000 -5.232219 -9.057590 -15.719318 -27.892509 -38.541042	NO. 0.00000 0.000000 -5.23219 -9.057590 -15.719318 -27.892509 -38.541042 -49.121807	NO. AERO PHASE 0.00000 -5.2219 -9.057590 -15.719318 -27.892509 -38.541942 -49.121807 -52.943192	NO. 0.00000 0.000000 -5.2319 -9.057590 -15.719318 -27.892509 -38.541042 -49.121807 -52.943192

1 Report No NASA CR-185135	2. Government Accessio	on No. 3. Recipient's Catalog No.
4 Title and Subtitle An Investigation of Counter	rotating Tip Vortex In	5. Report Date October 1989 6. Performing Organization Code
7 Author(s) R.K. Majjigi, K. Uenishi, a	nd P.R. Gliebe	Performing Organization Report No.      Work Unit No.
9 Performing Organization Name and Ad GE Aircraft Engines 1 Neumann Way P.O. Box 156301 Cincinnati, OH 45215-6301 12 Sponsoring Agency Name and Address National Aeronautics and Sp Lewis Research Center Cleveland, Ohio 44135-3191	3	535-03-01 11 Contract or Grant No NAS3-24080 13 Type of Report and Period Covered Contractor Report (Topical) 14 Sponsoring Agency Code
'5 Supplementary Notes Project Manager: F. Humeni NASA Lewi	k, Propulsion Systems s Research Center	; Division
adapted for use with counter predictions made with and with this interaction effect. The	rotating open rotors. thout the tip vortex of his report documents the ey parametric studies	eveloped for compressors has been extended and Comparison of available acoustic data with model included illustrate the importance of the analytical modeling, a limited experimental pertaining to the tip vortex as a noise source terroating propellers.
17 Key Words (Suggested by Author(s))		18. Distribution Statement
Tip vortex, propeller noise noise	, counterrotation	Unclassified- Unlimited

20. Security Classif (of this page)

Unclassified

19 Security Classif (of this report)

Unclassified

21 No of Pages

122

22 Price

		,

•		
•		
•		
•		

•

÷